

UNITED STATES PATENT APPLICATION

FOR

METHOD AND APPARATUS  
FOR  
MULTIBOARD FIBER OPTIC MODULES  
AND  
FIBER OPTIC MODULE ARRAYS

Inventors:

EDWIN DAIR  
WENBIN JIANG  
CHENG PING WEI

Prepared by:

BLAKELY SOKOLOFF TAYLOR & ZAFMAN LLP  
12400 Wilshire Boulevard, Seventh Floor  
Los Angeles, CA 90025-1026  
(714) 557-3800

METHOD AND APPARATUS  
FOR  
MULTIBOARD FIBER OPTIC MODULES  
AND  
FIBER OPTIC MODULE ARRAYS

5

CROSS REFERENCE TO RELATED APPLICATIONS

This application is a continuation-in-part application and claims the benefit of U.S. Application No. 09/321,308, Attorney Docket No. 003918.P002X, filed May 27, 1999 by inventors Wenbin Jiang et al, both of which are to be assigned to E2O Communications, Inc.

This application is also related to U.S. Application No. 09/320,409, Attorney Docket No. 003918.P002, filed May 26, 1999 by inventors Wenbin Jiang et al, and U.S. Application No. \_\_\_\_\_, Attorney Docket No. 003918.P002X2, filed March 22, 2001 by inventors Wenbin Jiang et al both of which are also to be assigned to E2O Communications, Inc.

20

FIELD OF THE INVENTION

This invention relates to fiber optic modules.

BACKGROUND OF THE INVENTION

Fiber optic modules interface optical fibers to electronic circuitry transducing communication by light or photons with communication by electrical signals. A fiber optic module may be a fiber optic receiver, transmitter or transceiver including both receive and transmit functions. The fiber optic receiver, transmitter and transceiver each have optical elements (OE) and electrical elements (EE). The fiber optic transmitter OE includes an emitter (such as a semiconductor LED or Laser) mounted in a package and an optical coupling element for coupling light or photons from

the OE into the optical fiber. The type of semiconductor laser (light amplification by stimulated emission of radiation) may be a vertical cavity surface emitting laser (VCSEL). The fiber optic receiver OE includes a photodetector (such as a photodiode) mounted in a package and an optical coupling element for coupling light or photons from the optical fiber into the photodetector. The EE for each includes integrated circuits and passive elements mounted on a substrate such as a printed circuit board (PCB) or ceramic.

10 The OE and EE are connected electrically at the emitter and photodetector.

Because of the high transmission frequencies utilized in fiber optic communication, crosstalk between receive and transmit signals is of concern. Additionally, electromagnetic interference (EMI) is of concern due to the high frequency of operation of the fiber optic modules. In order to reduce EMI, shielding of the electrical components is required which is usually accomplished by attaching a metal shield to the substrate of the fiber optic module and connecting it to ground. In order to avoid electronic crosstalk and EMI, the fiber optic transceiver usually employs separate components and separate shielding of fiber optic receiver and fiber optic transmitter components. In order to avoid optical crosstalk where light or photons can interfere between communication channels, the fiber optic transceiver usually employs separate optical elements for coupling light or photons into and out of the optical fiber for fiber optic receiver and fiber optic transmitter. Using separate optical elements requires additional components and increases the costs of fiber optic transceivers. It is desirable to reduce the component count of fiber optic transceivers such that they are less expensive to manufacture.

The form factor or size of the fiber optic module is of

concern. Previously, the fiber optic transceiver, receiver, and transmitter utilized horizontal boards or substrates which mounted parallel with a system printed circuit board utilized significant footprint or board space. The horizontal boards

5 provided nearly zero optical crosstalk and minimal electronic crosstalk when properly shielded. However, the horizontal boards, parallel to the system printed circuit board, required large spacing between optical fiber connectors to make the connection to the optical fibers. While this may have been

10 satisfactory for early systems using minimal fiber optic communication, the trend is towards greater usage of fiber optic communication requiring improved connectivity and smaller optical fiber connectors to more densely pack them on a system printed circuit board. Thus, it is desirable to

15 minimize the size of system printed circuit boards (PCBs) and accordingly it is desirable to reduce the footprint of the fiber optic module which will attach to such system PCBs.

Additionally, the desire for tighter interconnect leads of fiber optic cables, restricts the size of the OE's. For  
20 example, in the common implementation using TO header and can, the header dimension of the interconnect lead is normally 5.6mm. In small form factor optical modules, such as the MT family, the two optical fibers are separated by a distance of only 0.75mm. This severely restricts the method of coupling

25 light or photons from the OE into and out of fiber optic cables.

## BRIEF DESCRIPTIONS OF THE DRAWINGS

Figure 1 is a simplified top cutaway view of a first embodiment of the invention.

5 Figure 2 is an exploded view of the first embodiment of the invention.

Figure 3A is a cross-sectional view from the top of the optic block for the first embodiment of the invention.

Figure 3B is a front side perspective view from the left of the optic block for the first embodiment of the invention.

10 Figure 3C is a frontal view of the optic block for the first embodiment of the invention.

Figure 3D is a back side perspective view from the right of the optic block for the first embodiment of the invention.

15 Figure 3E is a back view of the optic block for the first embodiment of the invention.

Figure 3F is a right side view of the optic block for the first embodiment of the invention.

Figure 3G is a left side view of the optic block for the first embodiment of the invention.

20 Figure 3H is a cross-sectional view of the optic block for the first embodiment of the invention.

Figure 3I is a magnified cross-sectional view of the alignment post of the optic block.

25 Figure 4 is a simplified top cutaway view of another embodiment of the invention.

Figure 5A is an exploded view of the embodiment of the invention of Figure 4.

Figure 5B is an exploded view of an alternate embodiment of the invention of Figure 4.

30 Figure 5C is an exploded view of another alternate embodiment of the invention of Figure 4.

Figure 5D is an exploded view of another alternate embodiment of the invention of Figure 4.

Figure 6A is a cross-sectional view from the top of the optic block for embodiments of the invention.

Figure 6B is a front side view of the optic block for the embodiments of the invention.

5 Figure 6C is a back side view of the optic block for the embodiments of the invention.

Figure 6D is a top side view of the optic block for the embodiments of the invention.

10 Figure 7A is a top view of a manufacturing step of the invention.

Figure 7B is a side view of a manufacturing step of the invention.

Figure 8A is an exploded view of another embodiment of the invention.

15 Figure 8B is perspective view of an alternate baseplate for embodiments of the invention.

Figure 8C is a rear cross sectional view of the assembled invention illustrated in Figure 8A.

20 Figure 9A is an exploded view of another embodiment of the invention.

Figure 9B is a rear cross sectional view of the assembled invention illustrated in Figure 9A.

Figure 9C illustrates an alternate embodiment of a single ground plane for a printed circuit board.

25 Figure 9D illustrates an alternate embodiment of a single ground plane for a printed circuit board.

Figure 9E illustrates an alternate embodiment of a ground plane sandwiched between layers in a multilayer printed circuit board.

30 Figure 10A is an exploded view of another embodiment of the invention.

Figure 10B is a rear cross sectional view of the assembled invention illustrated in Figure 10A.

Figure 11A is an exploded view of another embodiment of the invention.

Figure 11B is a rear cross sectional view of the assembled invention illustrated in Figure 11A.

5        Figure 12A is an exploded view of another embodiment of the invention.

Figure 12B is a rear cross sectional view of the assembled invention illustrated in Figure 12A.

Figure 13 illustrates a receive optical block and a  
10        transmit optical block as an alternative to a single optical block.

Figure 14A illustrates how the pin configuration of the fiber optic modules can plug into a socket on a host printed circuit board.

15        Figure 14B illustrates how a socket configuration of the fiber optic modules can plug into a socket on a host printed circuit board.

Figure 14C illustrates how a socket configuration of the fiber optic modules can horizontally plug into a socket on a  
20        host printed circuit board.

Figure 15A illustrates a bottom perspective view of an alternate embodiment of the shielded housing or cover and base of the invention.

Figure 15B illustrates a rear cross sectional view of  
25        the assembled invention illustrated in Figure 10A substituting the alternate embodiment of the shielded housing or cover of Figure 15A.

Figure 15C illustrates a rear cross sectional view of the alternate embodiment of the shielded housing or cover of  
30        Figure 15A.

Figure 15D illustrates a cross sectional view of another alternate embodiment of the shielded housing or cover.

Figure 15E illustrates a cross sectional view of another

alternate embodiment of the shielded housing or cover.

Figure 15F illustrates a cross sectional view of another alternate embodiment of the shielded housing or cover.

Figure 15G illustrates a cross sectional view of another alternate embodiment of the shielded housing or cover.

Figure 16A illustrates a rear cross sectional view of an assembled alternate embodiment of the invention.

Figure 16B illustrates a rear cross sectional view of an assembled alternate embodiment of the invention.

Figures 17A-17D illustrate rear cross sectional views of assembled alternate embodiments of the invention.

Figures 18A- 18B illustrate rear cross sectional views of assembled alternated embodiments of the invention.

Figures 19A-19B illustrate rear cross sectional views of assembled alternated embodiments of the invention.

Figures 20A-20F illustrate rear cross sectional views of assembled embodiments of the invention including a redundant transmitter or receiver channel.

Figures 21A-21H illustrate rear cross sectional views of alternate embodiments of the invention including multiple printed circuit boards.

Figure 22A illustrates a top perspective view of an assembled alternate embodiment of the invention including a miniature back plane.

Figure 22B illustrates a top cut-away view of the invention illustrated in 22A.

Figure 22C illustrates a front view of the embodiment of



the invention illustrated in Figure 22A showing a horizontal array of fiber optics communication channels.

Figures 23A-23C illustrate the electronic connection between printed circuit boards and the miniature back planes.

5

Figures 24A-24J illustrate alternate embodiments of the horizontal array of fiber optics channels.

Figures 25A-25I illustrate rear cross sectional views of assembled alternate embodiments of the invention illustrated in Figures 25A-25C.

Figures 25A illustrates a front view of a 2x2 array of fiber optic channels for an assembled alternate embodiment of the invention.

Figure 25B illustrates a cut-away side view of the invention of 25A.

Figure 25C illustrates a rear cut-away view of the invention illustrated in Figure 25A.

Figure 26A illustrates a rear cross sectional view of an end by end array fiber optic communication channels as an alternate embodiment of the invention.

Figure 26B illustrates a side cut-away view of the invention of Figure 26A.

Figure 27A illustrates a rear cross sectional view of an assembled alternate embodiment of the invention of Figure 26A.

Figure 27B illustrates a side view of the invention of

Figure 27A.

Figure 28 illustrates a view cross sectional view of an assembled alternate embodiment of the invention.

Figure 29 illustrates a rear cross sectional view of an assembled alternate embodiment of the invention.

3918P002XX4  
Exp. No. EL802872838US

## DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENT

In the following detailed description of the invention, numerous specific details are set forth in order to provide a thorough understanding of the invention. However, it will be obvious to one skilled in the art that the invention may be practiced without these specific details. In other instances well known methods, procedures, components, and circuits have not been described in detail so as not to unnecessarily obscure aspects of the invention.

The invention includes a method, apparatus and system for method, apparatus and system for vertical board construction of fiber optic transmitters, receivers and transceivers. Briefly, fiber optic transmitter and receiver electrical elements are implemented on at least two separate printed circuit boards (PCBs) in a fiber optic module. The separate boards are arranged within the fiber optic module to reduce the footprint of the fiber optic module. In one embodiment, bending light or photons through ninety degrees, the light transmitter (a packaged type of emitter) and a light receiver (a packaged type of photodetector) are each mounted substantially perpendicular to the transmit and receive boards respectively such that their active areas are nearly facing each other but offset. A single optical block can be used to implement lenses and reflecting surfaces to minimize manufacturing costs. In one embodiment, the light receiver and light transmitter are mounted offset from each other in the optical block in order to avoid optical cross talk. In a second embodiment, the light transmitter (emitter) and the light receiver (photodetector) are each mounted substantially parallel with the transmit and receive boards respectively, the optical axis of transmitter and receiver and the connection to the optical fibers. The separate receive and

transmit boards can be provided with ground planes in order to minimize electrical cross talk. Preferably the ground planes on the back sides of the printed circuit boards face each other. A module outer shielded housing or cover, manufactured out of metal or metal plated plastic, provides further shielding for EMI. The separate boards may be extended to support multiple channels or multiple parallel fibers such as in a ribbon optical fiber cable. Manufacturing steps of the boards for the fiber optic module are disclosed to provide reduced manufacturing costs.

Referring now to Figure 1, a simplified cutaway view of the first embodiment of the invention is illustrated. Figure 1 illustrates a fiber optic module 100 coupling to a pair of fiber optic cables 101. Fiber optic module 100 includes an optical block 102 and an electrical element 104. The optical block 102 may also be referred to as a nose, an optical port, an alignment block, an optical connector, an optical receptacle or receptacle. The optical block 102 can interface to an optical connector such as an LC, MT-RJ or VF-45 optical connector. The electrical element 104 includes a transmit printed circuit board (PCB) 106, a receive PCB 108, an optional internal shield 109, a light transmitter 110, a light receiver 111, and a shielded housing or cover 119. The light transmitter 110 and light receiver 111 are optoelectronic devices for communicating with optical fibers using light of various wavelengths or photons. An optoelectronic device is a device which can convert or transduce light or photons into an electrical signal or an electrical signal into light or photons. The transmitter 110 is a packaged emitter, that converts an electrical signal into emitting light or photons, such as a semiconductor laser or LED, preferably packaged in a TO can. The receiver 111 is a packaged photodetector, that detects or receives light or photons and converts it into an

electrical signal, such as a photo diode, preferably package in a TO can. However other packages, housings or covers, or optoelectronic devices for receiving and transmitting light or photon may be used for the receiver 111 or transmitter 110.

Each of the optoelectronic devices, receiver 111 and transmitter 110, have terminals. In one embodiment, terminals of one or more optoelectronic devices couple to thruholes of the PCB 106 or PCB 108 or both. In another embodiment, terminals of one or more optoelectronic devices couple to an edge connector of the PCB 106 or PCB 108 or both. In one embodiment, the transmit PCB 106 includes electrical components 112 (transmitter integrated circuit (laser driver), resistors, capacitors and other passive or active electrical components), pins 113, and a ground plane 114. The electrical components 112 control the transmitter 110 and buffer the data signal received from a system for transmission over an optical fiber. In one embodiment, the receive PCB 108 includes electrical components 116 (receiver integrated circuit (transimpedance amplifier and post amplifier), resistors, capacitors and other passive or active electrical components), pins 117, and a ground plane 118. The electrical components 116 control the receiver 111 and buffer the data signal received from an optical fiber. The ground planes 114 and 118 and the shielded housing or cover 119 are coupled to ground. In another embodiment, a pin header consisting of a dielectric medium that is molded over a plurality of pins, is used to couple to through holes in the PCB 108 or PCB 106. The electrical components 116 and pins 117 are sandwiched between the ground plane 118 and the shielding 119 to shunt electro-magnetic fields to ground and avoid crosstalk in the receive PCB 108. Electrical components 112 and pins 113 are sandwiched between the ground plane 114 and the shielded housing or cover 119 to shunt electro-magnetic fields

generated by these components to ground and avoid crosstalk in the transmit PCB 106. Optional internal shielding 109 further provides additional crosstalk protection between printed circuit boards. If ground planes 114 and 118 are not used, then internal shielding 109 is required to reduce the electromagnetic fields that may be generated.

The optical block 102 includes lenses 120-123 and reflectors 124-125. Lenses 120-123 may be any collimating lenses including aspheric lenses, ball lenses, and GRIN lenses. Lenses 121-123 may be symmetric (circular symmetry) or asymmetric to provide optical steering. Lens 123 is for collimating the light or photons diverging from the transmitter 110 and lens 122 is for focussing the collimated light or photons into an optical fiber. Lens 120 is for collimating the light or photons diverging out from the end of an optical fiber and lens 121 is for focusing the collimated light or photons into the receiver 111. Reflectors 124-125 may be facets formed in the optical block having angles to provide total internal reflection between the optical block material and the atmosphere. Preferably they are forty five degree angle facets. Alternatively, they may be facets coated with a reflective surface or mirror surface to reflect light or photons off the reflective coated surface or facets having an optical grating surface to reflect photons. The optical block 102 is preferably constructed of a thermoplastic or polycarbonate which is clear to the desired wavelengths of light or photons. The reflectors 124-125, lenses 120-123 and other elements of the optical block 102 described below are preferably formed through injection molding of the desired material.

Referring to Figure 2, an exploded diagram of the fiber optic module 100 is illustrated and its assembly is described.

Transmitter 110 is inserted into an opening 214 in the

optical block 102. Receiver 111 is inserted into an opening 213 in optical block 102. An epoxy is injected into top and bottom tacking holes 215 in order to hold the transmitter 110 and receiver 111 in openings 214 and 213 respectively. An MT alignment plate 201 has optical block alignment holes 216, an optical opening 217 and fiber optic connector alignment pins 218 for alignment purposes. The optical block holes 216 couple to optical block alignment pins in the optical block 102, not illustrated in Figure 2. The fiber optic connector alignment pins 218 are for aligning optical fibers that couple to the fiber optic module 100.

For coupling to a fiber optic connector, the fiber optic module 100 has a nose 202 and a nose shield 203. The nose 202 includes a optical fiber opening 222 and a latch opening 223. The latch opening 223 receives the optical fiber connector and holds the optical fiber substantially fixed in place and aligned with the optical opening 217 of the alignment plate 201. The nose shield 203 includes an opening 224 for insertion over the nose 202 and shield tabs 225 for coupling to the ground plane of the package. The nose shielding 203 further reduces EMI.

After assembling the nose pieces to the optical block 102, the transmitter 110 and receiver 111 may be aligned to provide optimal light or photon output and reception. Alignment of the transmitter 110 and receiver 111 in optical block 102 is performed by active alignment where the receiver 111 and transmitter 110 are powered up to detect and emit photons. The receiver 111 and transmitter 110 are properly aligned in the optical block 102 to provide maximum photon detection from or coupling into fiber 101. The tacking holes 215 extend into the openings 213 and 214 such that epoxy may poured in to hold the optoelectronic devices to the optical block. After alignment is complete, the epoxy is UV cured and

allowed to set such that the receiver 111 and transmitter 110 are substantially coupled to the optical block 102.

After the epoxy has set, the receive PCB 108 and the transmit PCB 106 may be attached to the receiver 111 and transmitter 110 respectively. Receiver thruholes 232 in the receive PCB 108 are aligned and slid over terminals 211 of the receiver 111. The terminals 211 are then soldered to make an electrical connection on the component side (opposite the side of the ground plane 118) of the receive PCB 108. Transmitter thruholes 233 in the transmit PCB 106 are aligned and then slid over the terminals 210 of the transmitter 110. The terminals 210 are then soldered to make an electrical connection on the component side (opposite the side of the ground plane 114) of transmit PCB 106. Ground planes 114 and 118 have sufficient material removed around the transmitter thruholes 233 and the receiver thruholes 232 respectively to avoid shorting the terminals of the transmitter 110 and receiver 111 to ground.

After coupling the PCBs 108 and 106 to the receiver 111 and transmitter 110 respectively, the assembly is inserted into the shielded housing or cover 119. The optional internal shield 109 is next assembled into the shielded housing or cover 119 between the PCBs 106 and 108. The optional internal shield 109 has pin slots 230 to surround the pins 113 and 117 and avoid shorting thereto.

The shielded housing or cover 119 includes clips or tabs 236 at each corner for mating to a base 205. The base 205 includes PCB slots 240, clip openings or slots 238 into which the clips or tabs 236 may be inserted, and base pin holes 242 into which the PCB pins 113 and 117 may be inserted. The base 205 includes a guide post 244 for mounting the fiber optic module into a system printed circuit board. The bottom of the



base mounts parallel to the printed circuit board of the system such that when horizontal, the receive PCB 108 and the transmit PCB 106 are vertical and substantially perpendicular in reference to the printed circuit board of the system and the base 205. Next in assembly, the base 205 has its base pin holes 242 slid over the PCB pins 113 and 117, the printed circuit boards 106 and 108 are guided to mate with the PCB slots 240, and the clips or tabs 236 of the shielded housing or cover 119 are guided into the clip openings or slots 238. The receive PCB pins 113 and the transmit PCB pins 117 are vertical and substantially perpendicular in reference to the printed circuit board of the system and the base 205. After coupling the base 205 to the shielded housing or cover 119, the clips or tabs 236 are bent, twisted, or otherwise changed in order to hold the base 205 in place. As an alternative to clips or tabs 236 and clip openings or slots 238, the shielded housing or cover 119 may use plastic clips, or a ridge, integrated into each side that couples to base 205 appropriately. The shielded housing or cover 119, which is coupled to ground, encases the PCBs 106 and 108 to reduce the electro-magnetic fields generated by the electrical components coupled thereto by shunting the electric fields to ground to reduce electromagnetic interference (EMI).

Referring now to Figure 3A, a cross-sectional view of the optical block 102 for the first embodiment is illustrated.

The transmitter 110, the receiver 111, and the MT alignment plate 201 are coupled to the optical block 102. The light transmitter 110 includes an emitter 302 for generation of light or photons in response to electrical signals from the transmit PCB 106. The light receiver 111 includes a detector 304 to receive light or photons and generate electrical signals in response to light or photons coupled thereto. Light or photons emitted by the emitter 302 are coupled into

lens 123 and collimated onto the reflector 125 at an incident angle I1 (angle with the perpendicular to reflector 125 surface) preferably of substantially forty five degrees. Reflector 125 reflects the incident light or photons on a refraction angle R1 (angle with the perpendicular to reflector 125 surface) equivalent to incident angle I1 preferably of substantially forty five degrees. The reflected light or photons preferably travel perpendicular to the incident light or photons towards the lens 122. Lens 122 focuses the light or photons from the emitter 302 into an aligned optical fiber through the optical port 217 in the MT alignment plate 201. Thus, light or photons coupled or launched into an optical fiber, defining a first optical axis, are preferably substantially perpendicular to the light or photons emitted and incident upon lens 123 from the emitter 302 of the transmitter 110.

Light or photons, incident from a fiber optic cable coupled to the fiber optic module 100, is received through the optical port 217 of the MT alignment plate 201. Light or photons from the fiber optic cable are aligned to be incident upon the lens 120. Lens 120 collimates the incident light or photons from a fiber optic cable onto the reflector 124 at an incident angle I2 of preferably substantially forty five degrees. Reflector 124 reflects incident light or photons at a refractive angle R2 equivalent to incident angle I2 of preferably substantially forty five degrees towards lens 121.

Lens 121 focuses the light or photons received from a fiber optical cable onto the detector 304. Light or photons incident from a fiber optic cable, defining a second optical axis, are preferably substantially perpendicular to the light or photons incident upon the detector 304.

Figure 3B illustrates a frontal perspective view from the left side of the optical block 102. The front side of the

optical block 102 includes optical block alignment pins 316 and an optical output opening 317. The optical block alignment pins 316 couple to the alignment holes 216 of the alignment plate 201 such that the optical output opening 317 is aligned with the optical port 217 in the alignment plate 201. Figure 3C illustrates the front side of the optical block 102. The optical output opening 317 is indicated.

Figure 3D is a back side perspective view from the right of the optical block 102. The back side of the optical block 102 includes a cavity 322 that is used to form the shape of the reflective surfaces 124-125 during manufacturing of the optical block 102. Figure 3E is a back view of the optic block illustrating the opening into the cavity 322.

Figure 3F illustrates the right side of the optical block 102 which has the opening 214 to mate with the type of housing of the transmitter 110. The lens 123 can be viewed near the center of the opening 214. Figure 3G illustrates the left side of the optical block 102, which has the opening 213 to mate with the type of housing of the receiver 111. The lens 121 can be viewed near the center of the opening 213. Comparing Figures 3F and 3G, the offset between openings 213 and 214 to avoid optical crosstalk is visible. In the preferred embodiment, receiver 111 is closer to the optical opening 317 in order to minimize the loss of incoming received optical power. However, the position of receiver 111 and transmitter 110 can be interchanged. Figure 3H is a cross-sectional view of the optical block 102 illustrating the relative position of the optical block alignment posts 316. The area 324 surrounding the alignment post 316 is magnified in Figure 3I. Figure 3I provides a magnified cross-sectional view of the alignment post 316.

Figure 4 illustrates another embodiment of the

invention. To couple to the optical fibers 101, a fiber optic module 400 includes an optical block 402 and electrical elements 404. The optical block 402 may also be referred to as a nose, an optical port, an alignment block, an optical connector, an optical receptacle or receptacle. The optical block 402 can interface to an optical connector such as an LC, MT-RJ or VF-45 optical connector. Electrical elements 404 include transmitter PCB 106, receiver PCB 108, light receiver 111, light transmitter 110, and a shielded housing or cover 419. Shielded housing or cover 419 may be narrower than shielded housing or cover 119 due to receiver 111 and transmitter 110 being parallel with the PCBs 108 and 106. The optical or alignment block 402 may include lens 423 and lens 421 for coupling light or photons into and out of the fiber optic cable 101. Alternatively the lens 423 and 421 may be coupled to the receiver 111 and transmitter 110. Lens 423 and 421 may be spherical lenses or each may be a pair of aspheric lenses on the same optical axis. Light or photons emitted by the transmitter 110 are collected and focused by lens 423 into a transmit fiber optic cable. Light or photons on a receive fiber optic cable are collected and focused by lens 421 into the receiver 111. In this manner, fiber optic module 400 preferably keeps light or photons substantially in parallel and does not have to reflect the light or photons to couple it with receiver 111 or transmitter 110.

Figure 5A illustrates an exploded diagram of the fiber optic module 400. Fiber optic module 400 is assembled similar to fiber optic module 100 as previously described with reference to Figure 2. However, optical or alignment block 402 differs from optical block 102. Receiver 111 and transmitter 110 are inserted into openings 513 and 514 respectively in the optical or alignment block 402. The receiver and transmitter may be held in place by a press fit

or glued in place. To glue in place, an epoxy or glue is injected in top and bottom tacking holes 515 of the optical or alignment block 402 while the receiver 111 and transmitter 110 are tested and aligned to substantially couple light or photons into and out of fiber optic cables. After the epoxy is set and the receiver and transmitter are substantially fixed in the optical block 102, the transmit PCB 106 and the receive PCB 108 are coupled respectively to the transmitter 110 and the receiver 111. The terminals 511 and 510 of the receiver 111 and the transmitter 110 respectively are soldered directly onto the PCB. The high frequency pins associated with the receiver 111 and transmitter 110 are preferably soldered on the component side of the printed circuit boards in order to provide proper shielding. The alignment plate 201, the nose 202 and the nose shielding 203 are unnecessary in this embodiment of the invention. Fiber ferrules are utilized instead for alignment between the optical or alignment block 402 and the optical fibers 101.

Referring now to Figure 5B, an exploded view of a fiber optic module 400' is illustrated. Fiber optic module 400' is assembled similar to fiber optic module 400 as previously described with reference to Figure 5A but a different base 205' is utilized. The base 205' differs from base 205 in that it has a pair of guide rails 540 to hold the PCBs 106 and 108 in place and a pair of cutouts or open slots 542 for the pins 113 and 117 to extend through. In this manner, the PCBs 106 and 108 may slide into place onto the base 205'.

Referring now to Figure 5C, an exploded view of a fiber optic module 400'' is illustrated. Fiber optic module 400'' is assembled similar to fiber optic module 400 as previously described with reference to Figure 5A but a different base 205'' is utilized. The base 205'' differs from base 205 in that it has pairs of mounting brackets 540' to hold the PCBs

106 and 108 in place and a pair of openings 542' for the pins 113 and 117 to extend through.

The PCB slots 240, guide rails 540 or brackets 540' can be replaced by slots, brackets or guide rails of the optical block 402 to align the PCBs thereto. Additionally, it is to be understood that alternate bases may be formed by combining the elements of the bases 205, 205', and 205'' in different ways. For example, refer to Figure 5D. Figure 5D illustrates an exploded view of a fiber optic module 400'''. Fiber optic module 400''' is assembled similar to fiber optic module 400 as previously described with reference to Figure 5A but a different base 205''' is utilized and a slightly different optical block 502 is utilized. The base 205''' differs from base 205 in that there are no slots 240 and that there are a pair of cutouts or open slots 542 for the pins 113 and 117 to extend through. The optical block 502 differs from the optical block 402 in that a pair of slots 525 are provided to align the PCBs 106 and 108 with the optical block.

Referring now to Figure 6A, a cross-sectional view of the optical or alignment block 402 for the second embodiment is illustrated. The transmitter 110 and the receiver 111 are coupled to the optical or alignment block 402. The transmitter 110 includes an emitter 302 for generation of light or photons. The receiver 111 includes a detector 304 to receive light or photons. Light or photons emitted by the emitter 302 are coupled into lens 423, collected and focused into the optical fiber through the optical port 417A. Light or photons, incident from a fiber optic cable coupled to the fiber optic module 400, is received through the optical port 417B. Photons from the fiber optic cable are incident upon the lens 421. Lens 421 collects and focuses the incident light or photons from the fiber optic cable onto the detector 304 of the receiver 111. In order to keep the optical fibers

101 in alignment with the optical or alignment block 402, a pair of fiber ferrules 421 are provided. The fiber ferrules 421 are inserted into the optical ports 417A and 417B.

Figure 6B illustrates the front side of the optical or alignment block 402. The front side of the optical or alignment block 402 includes optical output ports 417A and 417B. In Figure 6B, the lens 421 is visible through the optical output port 417B and lens 423 is visible through the optical output port 417A. Figure 6C is an illustration of the back side of the optical or alignment block 402. In Figure 6C, the lens 421 is visible through opening 513 and lens 423 is visible through opening 514. Figure 6D illustrates the top side of the optical or alignment block 402 which has the tacking holes 515 coupling to the openings 513 and 514. Epoxy may be inserted into the top and bottom tacking holes 515 to hold the transmitter 110 and receiver 111 in position in the optical or alignment block 402.

Referring now to Figures 7A-7B, final steps of the assembly of printed circuit boards 106 and 108 are illustrated. Transmit PCB 106 and receive PCB 108 are assembled as one unit on one printed circuit board 700 with a center score 702 defining a boundary line between transmit and receive components. After all components have been attached and assembled onto the unitary PCB 700, the PCB 700 is flexed along the score 702 such that the transmit PCB 106 and the receive PCB 108 may be separated. Transmit PCB 106 and the receive PCB 108 may thereafter be assembled as part of the fiber optic module 100 and the fiber optic module 400. The transmit PCB 106 and the receive PCB 108 may each be approximately 6.5 mm in height excluding pins 113 and 117.

Referring now to Figure 8A, another embodiment of the invention is illustrated. Figure 8A illustrates an exploded

view of a fiber optic module 800. The fiber optic module 800 includes an upper transmit PCB 106U, a lower transmit PCB 106L, an upper receive PCB 108U, a lower receive PCB 108L, the transmitter 110, the receiver 111, the optical block 402, the shielded housing or cover 419, a first and second PCB interconnect pin headers 827, a first terminal pin header 813 for the transmitter, a second terminal pin header 817 for the receiver, and a baseplate 805.

The transmitter 110 is a transmit optical subassembly (Tx OSA) that includes a VCSEL or other semiconductor device that transduces electrical signals into photons or a light output.

The receiver 111 is a receive optical subassembly (Rx OSA) including a PIN diode or other device that converts photons or light input into electrical signals. The Tx OSA and Rx OSA are attached to physically separated transmit and receive electrical subassemblies (ESA's). In one embodiment, the transmit ESA includes an upper and lower transmit PCBs 106U and 106L with components 116 mounted thereto. In one embodiment, the receive ESA includes an upper and lower receive PCBs 108U and 108L with components 112 mounted thereto.

The lower transmit PCB 106L and the upper transmit PCB 106U provide similar functionality to that of the transmit PCB 106 and include components 112. The lower receive PCB 108L and the upper receive PCB 108U provide similar functionality to that of the receive PCB 108 and include components 116. The upper and lower transmit PCBs 106U and 106L are parallel to each other in a horizontal plane and parallel with the optical axis of the transmitter 110. The upper and lower receive PCBs 108U and 108L are parallel to each other in a horizontal plane and parallel with the optical axis of the receiver 111. This configuration of parallel horizontal



boards for each of the transmit and receive capability can be referred to as dual-stack horizontal modular PCBs.

The first and second pin interconnect headers 827 include the conductive signal pins 837 molded into a non-conductive medium. The first and second pin interconnect headers 827 are used to interconnect lower and upper PCB's. The first pin header 827 provides signal interconnection between the upper and lower transmit PCBs 106U and 106L. The first pin header 827 provides signal interconnection between the upper and lower transmit PCBs 106U and 106L. The second pin header 827 provides signal interconnection between the upper and lower receive PCBs 108U and 108L. The second pin header 827 has pins 837 that couple into upper throughholes 847U in the upper receive PCB 108U and lower through holes 847L in the lower receive PCB 108L. The first pin header 827 similarly has pins 837 that couple into upper and lower throughholes in the upper and lower transmit PCBs 106U and 106L respectively.

The first and second terminal pin headers 817 and 813 include conductive signal pins molded into a non-conductive medium. The first and second terminal pin headers 817 and 813 are used to route electrical signals to and from the fiber optic module 800 to a host system. The first terminal pin header 813 has pins 113 that couple to through holes 842 in the lower transmit PCB 106L. Similarly, the second terminal pin header 817 has pins 117 that couple to through holes 842 in the lower receive PCB 108L.

The transmitter 110 couples to the upper transmit PCB 106U in one embodiment. The terminals 810 of the transmitter 110 couple to the upper transmit PCB 106U in one embodiment. Using a straddle mount, one or more terminals couple to upper edge traces 820U on a top side of the upper transmit PCB 106U and one or more terminals couple to lower edge traces 820L on

a back side of the upper transmit PCB 106U. In a straddle mount, the optoelectronic device (i.e. the transmitter 110 or the receiver 111) has its optical axis nearly in-line and parallel with a plane of the printed circuit board. In an alternate embodiment, the terminals 810 may couple to the lower transmit PCB 106U. In another alternate embodiment, the terminals 810 may couple between the upper and lower receive PCBs so that one or more couple to the upper PCB and one or more couple to the lower PCB. In yet another alternate embodiment using a through hole mount, the terminals 810 may couple into holes of the upper or lower transmit PCBs or both upper and lower transmit PCBs. In a through hole mount, the optoelectronic device (i.e. the transmitter 110 or the receiver 111) has its optical axis nearly parallel with a plane of the printed circuit board.

The receiver 111 couples to the upper receive PCB 108U in one embodiment. The terminals 811 of the receiver 111 couple to the upper receive PCB 108U in one embodiment. Using a straddle mount, one or more terminals couple to upper edge traces 821U on a top side of the upper receive PCB 108U and one or more terminals couple to lower edge traces 821L on a back side of the upper receive PCB 108U. In an alternate embodiment, the terminals 811 may couple to the lower receive PCB 108U. In another alternate embodiment, the terminals 811 may couple between the upper and lower receive PCBs so that one or more couple to the upper PCB and one or more couple to the lower PCB. In yet another alternate embodiment, the terminals 811 may couple into holes of the upper or lower receive PCBs or both upper and lower receive PCBs.

Included with the fiber optic module 800 is a baseplate 805. The baseplate 805 may include an inner septum 815 that divides the transceiver and receiver into two separate cavities, for EMI and electrical isolation of the transmitter

from the receiver or between channels. The baseplate 805 acts like a chassis or frame to provide support for the shielded housing or cover 419 and the receiver and transmit subassemblies. The baseplate 805 may include an inner septum 815, one or more openings 242 to receive the pins 113 and 117, and one or more clip openings or slots 238 to receive the clips or tabs 236. The baseplate 805 in one embodiment is plastic in other embodiments that baseplate may be metal or a metalized plastic to provide shielding. The inner septum 815 provides separation between the transmitter and the receiver or between channels.

Referring now to Figure 8B, an alternate baseplate 805' is illustrated. Baseplate 805' differs from baseplate 805 in that it includes slots 842 for pins 113 and 117. Baseplate 805' may similarly include clip openings or slots 238 and the inner septum 815.

Referring now to Figure 8C, a rear cross sectional view of the assembled fiber optic module 800 is illustrated. The baseplate 805 with the inner septum 815 can divide the fiber optic module 800 into two separate cavities. The separate cavities can improve EMI and electrical isolation of the transmitter from the receiver. The receiver 111 couples to the upper receive PCB 108U with its terminals 811 using a straddle mount in one embodiment. The transmitter 111 couples to the upper transmit PCB 106U with its terminals 810 using a straddle mount in one embodiment.

In Figure 8C, the upper and lower transmit PCBs 106U and 106L are parallel to each other in a horizontal plane and parallel with the optical axis of the transmitter 110. The upper and lower receive PCBs 108U and 108L are parallel to each other in a horizontal plane and parallel with the optical axis of the receiver 111. This configuration of parallel

horizontal boards for each channel can be referred to as dual-stack horizontal modular PCBs. The dual stacked horizontal PCB's allow an increase in component surface mounting area for a given volume. Both sides of the upper and lower transmit and receive PCB's can be utilized to mount electronic components. This increased surface area can provide increased functionality in a fiber optic module by allowing additional components such as integrated circuits and passive components such as filters, capacitors, and inductors to be utilized.

Referring now to Figure 9A, another embodiment of the invention is illustrated. Figure 9A illustrates an exploded view of a fiber optic module 900. The fiber optic module 900 utilizes a motherboard which is common to daughtercards PCBs which are substantially perpendicular to the motherboard. Assuming the motherboard is horizontal, the daughtercard PCBs are substantially vertical to the motherboard and can be also be referred to as vertical PCBs. The substantially vertical PCB's couple to the common motherboard.

The fiber optic module 900 includes a vertical transmit PCB 106' and a vertical receive PCB 108' in parallel coupled to a horizontal motherboard PCB 905. The motherboard PCB 905 can separate ground and power planes between receiver and transmitter channels in order to maximize isolation and minimize cross talk. The vertical transmit PCB and the vertical receive PCB may have traces soldered to traces of the motherboard for electrical connectivity or otherwise include pins that plugged into holes or sockets of the motherboard to ease replacement or to expand the number of transmit or receive channels with additional transmit PCBs or receive PCBs. Alternatively, the electrical connection between the vertical transmit PCB and the vertical receive PCB and motherboard PCB may be made with electrical connectors in lieu

of solder joints. The mother board PCB includes Input/Output Pins (I/O Pins) or an I/O socket connector to couple to holes or a socket of a host system PCB to interface with a host system.

In order to further minimize the form factor of the fiber optic module 900, the vertical transmit PCB and the vertical receive PCB provides mounting surfaces for components on both the left and right side surfaces (or front and back surfaces).

Additionally, a top surface of the motherboard PCB 905 may also be used to mount components or circuits for increased electrical functionality such as a clock/data recovery (CDR) function and minimize the form factor of the fiber optic module.

To minimize EMI and crosstalk between the vertical transmit PCB and the vertical receive PCB, an inner shield similar to the shield 109 may be used. Alternatively, one or both of the vertical transmit PCB and the vertical receive PCB may have a ground plane on of its left or right side surfaces (sometimes referred to as a backside ground plane).

The vertical PCBs 106' and 108' are similar to PCBs 106 and 108 but for the coupling to the horizontal motherboard PCB 905. The vertical PCBs 106' and 108' have signal traces soldered to signal traces of the horizontal motherboard PCB 905 which can also mechanically support the vertical PCBs 106' and 108'. Solder joints 917R couple the receive PCB 108' to the horizontal motherboard PCB 905. Solder joints 917T couple the transmit PCB 106' to the horizontal motherboard PCB 905 (see Figure 9B). The fiber optic module 900 can be referred to as having vertical PCB's with a horizontal motherboard PCB.

The horizontal motherboard PCB 905 includes input/output (I/O) pins 113 and 117 to couple to a host system and wire traces to route power, ground and signals between the pins 113

and 117 and the vertical PCBs 106' and 108'.

The fiber optic module 900 further includes the transmitter 110, the receiver 111, the optical block 402, and the shielded housing or cover 419. The shielded housing or cover 419 has clips or tabs 236 that couple into clip openings or slots 238 in the motherboard PCB 905. The clips or tabs 236 can be held in place in the slots by a friction fit or glued in place or they may extend through the motherboard PCB 905 and be turned and or bent to couple the shielded housing or cover 419 and the motherboard PCB 905 together. Alternatively, the clips or tabs 236 of the shielded housing or cover 419 can wrap around the motherboard PCB 905 to couple them together.

The transmitter 110 couples into the opening 514 of the optical block 402. The receiver 111 couples into the opening 513 of the optical block. They are held in place by either a friction fit or a glue such as an epoxy.

The transmitter 110 couples to the transmit PCB 106'. The terminals 810 of the transmitter 110 couple to the transmit PCB 106'. In one embodiment using a straddle mount, one or more terminals 810 couple to left edge traces 920L on a left side and one or more terminals 810 couple to right edge traces 920R on a right side of the transmit PCB 106'. In alternate embodiment, the terminals 810 may couple to one side of the transmit PCB 106'. In yet another alternate embodiment, the terminals 810 may couple into holes of the transmit PCB 106'.

The receiver 111 couples to the receive PCB 108'. The terminals 811 of the receiver 111 couple to the receive PCB 108'. Using a straddle mount, one or more terminals 811 couple to left edge traces 921L on a left side and one or more terminals 811 couple to right edge traces 921R on a right side

of the receive PCB 108'. In an alternate embodiment, the terminals 811 may couple to one side of the receive PCB 108'.

In yet another alternate embodiment, the terminals 811 may couple into holes of the receive PCB 108'.

Referring now to Figure 9B, a rear cross-sectional view of the assembled fiber optic module 900 is illustrated. Traces 920 on the motherboard PCB route signals to components on the motherboard PCB, the I/O pins 113 and 117, and the solder joints 917R and 917T. A ground plane 118 can be coupled to a side the vertical receive PCB 108' or a ground plane 114 can be coupled to a side of the vertical transmit PCB 106' or both. Referring to Figure 9C, the vertical transmit PCB 106' includes the ground plane 114 and the vertical receive PCB 108' is without a ground plane to allow room for added components 116 on each side. Referring to Figure 9D, the vertical receive PCB 108' includes the ground plane 118 and the vertical transmit PCB 106' is without a ground plane to allow room for added components 112 on each side. An optional inner shield 109 can also be used for further isolation between channels to reduce cross-talk and EMI as illustrated in Figure 9B. In any case, the ground plane 114 and 118 will have cutouts for traces to coupled to the terminals 810 and 811 and may have additional cutouts for components 112 or 116 as the case may be. Referring now to Figure 9E, the ground plane 118 or the ground plane 114 may be alternatively sandwiched between layers of either the vertical receive PCB 108' or the vertical transmit PCB 106' or both as a part of a multilayer PCB as illustrated by Figure 9C. This can allow for further components 116 and 112 to be added to both sides of the vertical receive PCB 108' and the vertical transmit PCB 106'.

Referring now to Figure 10A, another embodiment of the invention is illustrated. Figure 10A illustrates an exploded

view of a fiber optic module 1000. The fiber optic module 1000 has angled PCBs with respect to a horizontal or vertical axis of the fiber optic module 1000. The length of the PCBs remain parallel to the optical axis of the receiver 111 and transmitter 110. By angling the PCBs with the horizontal or vertical axis, the PCBs may be made smaller to fit a smaller form factor or alternatively the surface area can be increased. That is the available PCB surface area for mounting components can be increased for a given volume by angling the PCBs. The increased surface area can give the final assembled fiber optic module increased functionality by allowing components such as integrated circuits and passive components such as filters, capacitors, and inductors to be added. More room can also be provided in the fiber optic module 1000 for mounting larger components by angling the PCBs.

The fiber optic module 1000 includes an angled transmit PCB 106'', an angled receive PCB 108'', the transmitter 110, the receiver 111, an optical block 402', the shielded housing or cover 419, a first terminal pin header 1027T for the transmitter, a second terminal pin header 1027R for the receiver, and the baseplate 805 or 805'.

The angled transmit PCB 106'' and the angled receive PCB 108'' are arranged within the fiber optic module at an angle with respect to the horizontal axis thereof as defined by a line normal to both receiver and transmitter optical axes. The angled transmit PCB 106'' and the angled receive PCB 108'' are held in place having a width that is on an angle with respect to a horizontal or vertical axis of the fiber optic module 1000. The length of the angled transmit PCB 106'' and the angled receive PCB 108'' are parallel to the optical axis of the receiver 111 and transmitter 110. The angled transmit PCB 106'' includes components 116 and left and right edge



traces 921L and 921R. The first terminal pin header 1027T has pins 117 that couple to holes of the angled transmit PCB 106'' on one end. The angled receive PCB 108'' includes components 112 and left and right edge traces 920L and 920R. The second terminal pin header 1027R has pins 113 that couple to holes of the angled receive PCB 108'' on one end.

The transmitter 110 is a transmit optical subassembly (Tx OSA) that includes a VCSEL or other semiconductor device that transduces electrical signals into photons or a light output.

The receiver 111 is a receive optical subassembly (Rx OSA) including a PIN diode or other device that converts photons or light input into electrical signals. The Tx OSA and Rx OSA are attached to physically separated transmit and receive electrical subassemblies (ESA's). In one embodiment, the transmit ESA includes the angled transmit PCB 106'' with components 116 and the first terminal pin header 1027T mounted thereto. In one embodiment, the receive ESA includes the angled receive PCB 108'' with components 112 and the second terminal pin header 1027R mounted thereto.

The optical block 402' is similar to the optical block 402 but has some modifications to accommodate the angled transmit PCB 106'' and the angled receive PCB 108''. The optical block 402' includes openings 513' and 514' to receive the receiver 111 and transmitter 110 respectively and angled slots 1015 to receive the angled transmit PCB 106'' and the angled receive PCB 108''. The angled slots 1015 can provide a friction fit with the angled transmit PCB 106'' and the angled receive PCB 108'' or glue or epoxy can be used to couple them together. The angled slots 1015 can also serve to tack the receiver 111 and transmitter 110 in place within the optical block 402'.

The transmitter 110 couples into the opening 514' of the

optical block 402'. The receiver 111 couples into the opening 513' of the optical block 402'. They can be held in place by either a friction fit or a glue such as an epoxy.

The transmitter 110 also couples to the transmit PCB 106''. The terminals 810 of the transmitter 110 couple to the transmit PCB 106'' in one embodiment. Using a straddle mount, one or more terminals 810 couple to left edge traces 920L on a left side and one or more terminals 810 couple to right edge traces 920R on a right side of the transmit PCB 106''. In an alternate embodiment, the terminals 810 may couple to one side of the transmit PCB 106''. In yet another alternate embodiment, the terminals 810 may couple into holes of the transmit PCB 106''.

The receiver 111 also couples to the receive PCB 108''. The terminals 811 of the receiver 111 couple to the receive PCB 108''. Using a straddle mount, one or more terminals 811 couple to left edge traces 921L on a left side and one or more terminals 811 couple to right edge traces 921R on a right side of the receive PCB 108''. In an alternate embodiment, the terminals 811 may couple to one side of the receive PCB 108''. In yet another alternate embodiment, the terminals 811 may couple into holes of the receive PCB 108''.

Referring now to Figure 10B, a rear cross-sectional view of the assembled fiber optic module 1000 is illustrated. The first terminal pin header 1027T is coupled to the angled transmit PCB 1027T so that pins 117 are vertical with the reference axis. The second terminal pin header 1027R is coupled to the angled receive PCB 108'' so that pins 113 are vertical with the reference axis. A ground plane 118 can be coupled to a side the angled receive PCB 108'' or a ground plane 114 can be coupled to a side of the angled transmit PCB 106'' or both similar to previously described with reference

to the vertical boards and Figures 9B-9E. The shield housing or cover 419 couples to the base or baseplate 805 or 805' around the printed circuit boards. Depending upon the width of the printed circuit boards 106' and 108' and the width of the fiber optic module 1000, the angles  $\theta 1$  and  $\theta 2$  which the printed boards make with the base or baseplate 805 or 805' can vary between zero and ninety degrees.

Referring now to Figure 11A, another embodiment of the invention is illustrated. Figure 11A illustrates an exploded view of a fiber optic module 1100. The fiber optic module 1100 has parallel angled or slanted PCBs with respect to a horizontal or vertical axis of the fiber optic module 1100. The length of the PCBs remain parallel to the optical axis of the receiver 111 and transmitter 110. By parallel angling the PCBs with the horizontal or vertical axis, the PCBs may be made smaller to fit a smaller form factor or alternatively the surface area can be increased. That is the available PCB surface area for mounting components can be increased for a given volume by angling the PCBs. The increased surface area can give the final assembled fiber optic module increased functionality by allowing components such as integrated circuits and passive components such as filters, capacitors, and inductors to be added. More room can also be provided in the fiber optic module 1100 for mounting larger components by angling the PCBs in parallel together.

The fiber optic module 1100 includes an angled transmit PCB 106'', an angled receive PCB 108'', the transmitter 110, the receiver 111, an optical block 402'', the shielded housing or cover 419, a first terminal pin header 1027T' for the transmitter, a second terminal pin header 1027R' for the receiver, and a baseplate 805''.

The angled transmit PCB 106'' and the angled receive PCB

108''' are arranged in parallel and at an angle with respect to a horizontal datum plane that passes through and is normal to receiver and transmitter optical axes. The angled transmit PCB 106''' and the angled receive PCB 108''' are slanted in parallel to the right but can be easily arranged so as to slant in parallel to the left. The angled transmit PCB 106''' and the angled receive PCB 108''' are held in place having a width that is on an angle with respect to a horizontal or vertical axis of the fiber optic module 1100. The length of the angled transmit PCB 106''' and the angled receive PCB 108''' are parallel to the optical axis of the receiver 111 and transmitter 110. The angled transmit PCB 106''' includes components 116 and left and right edge traces 921L and 921R. The first terminal pin header 1027T' has pins 117 that couple to holes of the angled transmit PCB 106''' on one end. The angled receive PCB 108''' includes components 112 and left and right edge traces 920L and 920R. The second terminal pin header 1027R' has pins 113 that couple to holes of the angled receive PCB 108''' on one end.

The transmitter 110 is a transmit optical subassembly (Tx OSA) that includes a VCSEL or other semiconductor device that transduces electrical signals into photons or a light output.

The receiver 111 is a receive optical subassembly (Rx OSA) including a PIN diode or other device that converts photons or light input into electrical signals. The Tx OSA and Rx OSA are attached to physically separated transmit and receive electrical subassemblies (ESA's). In one embodiment, the transmit ESA includes the angled transmit PCB 106''' with components 116 and the first terminal pin header 1027T' mounted thereto. In one embodiment, the receive ESA includes the angled receive PCB 108''' with components 112 and the second terminal pin header 1027R' mounted thereto.

The baseplate 805'' is similar to the baseplate 805 and

805' but has angled inner septum 815' to be angled in parallel with the angled transmit PCB 106''' and the angled receive PCB 108'''. The baseplates 805, 805', 805'' in one embodiment may be a dielectric to isolate components and insulate them from one another. In another embodiment, baseplates 805, 805', 805'' may be an insulator. In another embodiment, baseplates 805, 805', 805'' may have their septum 815 or 815' metalized so as to provide EMI and crosstalk shielding. Alternatively, a metal shield may be placed on top of the septum 815 or 815' such as shield 109.

The optical block 402'' is similar to the optical block 402 but has some modifications to accommodate the angled transmit PCB 106''' and the angled receive PCB 108'''. The optical block 402'' includes openings 513'' and 514'' to receive the receiver 111 and transmitter 110 respectively and angled slots 1115 to receive the angled transmit PCB 106''' and the angled receive PCB 108'''. The angled slots 1115 can provide a friction fit with the angled transmit PCB 106''' and the angled receive PCB 108''' or glue or epoxy can be used to couple them together. The angled slots 1115 can also serve to tack the receiver 111 and transmitter 110 in place within the optical block 402''.

The transmitter 110 couples into the opening 514'' of the optical block 402''. The receiver 111 couples into the opening 513'' of the optical block 402''. They can be held in place by either a friction fit or a glue such as an epoxy.

The transmitter 110 also couples to the transmit PCB 106'''. The terminals 810 of the transmitter 110 couple to the transmit PCB 106''' in one embodiment. Using a straddle mount, one or more terminals 810 couple to left edge traces 920L on a left side and one or more terminals 810 couple to right edge traces 920R on a right side of the transmit PCB

106''' . In an alternate embodiment, the terminals 810 may couple to one side of the transmit PCB 106''' . In yet another alternate embodiment, the terminals 810 may couple into holes of the transmit PCB 106''' .

The receiver 111 also couples to the receive PCB 108''' . The terminals 811 of the receiver 111 couple to the receive PCB 108''' . Using a straddle mount, one or more terminals 811 couple to left edge traces 921L on a left side and one or more terminals 811 couple to right edge traces 921R on a right side of the receive PCB 108''' . In an alternate embodiment, the terminals 811 may couple to one side of the receive PCB 108''' . In yet another alternate embodiment, the terminals 811 may couple into holes of the receive PCB 108''' .

Referring now to Figure 11B, a rear cross-sectional view of the assembled fiber optic module 1100 is illustrated. The angled receive PCB 108''' and the angled transmit PCB 106''' of the fiber optic module 1100 are angled in parallel together with respect to a horizontal or vertical axis thereof. The first terminal pin header 1027T' is coupled to the angled transmit PCB 1027T' so that pins 117 are vertical with the reference axis. The second terminal pin header 1027R' is coupled to the angled receive PCB 108''' so that pins 113 are vertical with the reference axis. A ground plane 118 can be coupled to a side the angled receive PCB 108''' or a ground plane 114 can be coupled to a side of the angled transmit PCB 106''' or both similar to previously described with reference to the vertical boards and Figures 9B-9E. The shield housing or cover 419 couples to the baseplate 805'' around the printed circuit boards. Depending upon the width of the printed circuit boards 106''' and 108''' and the width of the fiber optic module 1100, the angles  $\theta_3$  and  $\theta_4$  which the printed boards make with the base or baseplate 805'' and the angle  $\theta_5$

which the septum 815' makes with the base or baseplate 805' can vary between zero and ninety degrees.

Referring now to Figure 12A, another embodiment of the invention is illustrated. Figure 12A illustrates an exploded view of a fiber optic module 1200. The fiber optic module 1200 has angled or slanted PCBs with respect to a horizontal or vertical axis of the fiber optic module 1200. The PCBs are angled or slanted away at top edges to form a V configuration of PCB orientation. The length of the PCBs remain parallel to the optical axis of the receiver 111 and transmitter 110. By angling the PCBs with the horizontal or vertical axis, the PCBs may be made smaller to fit a smaller form factor or alternatively the surface area can be increased. That is the available PCB surface area for mounting components can be increased for a given volume by angling the PCBs. The increased surface area can give the final assembled fiber optic module increased functionality by allowing components such as integrated circuits and passive components such as filters, capacitors, and inductors to be added. More room can also be provided in the fiber optic module 1200 for mounting larger components by angling the PCBs.

The fiber optic module 1200 includes an angled transmit PCB 106''', an angled receive PCB 108''', the transmitter 110, the receiver 111, an optical block 402'', the shielded housing or cover 419, a first terminal pin header 1027T'' for the transmitter, a second terminal pin header 1027R'' for the receiver, and the baseplate 805 or 805'.

The angled transmit PCB 106'''' and the angled receive PCB 108'''' are arranged at an angle with respect to the horizontal axis of the fiber optic module as defined by a line normal to both receiver and transmitter optical axes. The angled transmit PCB 106'''' and the angled receive PCB 108''''

slant away from each other to form the V configuration. The angled transmit PCB 106'''' and the angled receive PCB 108'''' are held in place having a width that is on an angle with respect to a horizontal or vertical axis of the fiber optic module 1200. The length of the angled transmit PCB 106'''' and the angled receive PCB 108'''' are parallel to the optical axis of the receiver 111 and transmitter 110. The angled transmit PCB 106'''' includes components 116 and left and right edge traces 921L and 921R. The first terminal pin header 1027T'' has pins 117 that couple to holes of the angled transmit PCB 106'''' on one end. The angled receive PCB 108'''' includes components 112 and left and right edge traces 920L and 920R. The second terminal pin header 1027R'' has pins 113 that couple to holes of the angled receive PCB 108'''' on one end.

The transmitter 110 is a transmit optical subassembly (Tx OSA) that includes a VCSEL or other semiconductor device that transduces electrical signals into photons or a light output.

The receiver 111 is a receive optical subassembly (Rx OSA) including a PIN diode or other device that converts photons or light input into electrical signals. The Tx OSA and Rx OSA are attached to physically separated transmit and receive electrical subassemblies (ESA's). In one embodiment, the transmit ESA includes the angled transmit PCB 106'''' with components 116 and the first terminal pin header 1027T'' mounted thereto. In one embodiment, the receive ESA includes the angled receive PCB 108'''' with components 112 and the second terminal pin header 1027R'' mounted thereto.

The optical block 402''' is similar to the optical block 402 but has some modifications to accommodate the angled transmit PCB 106'''' and the angled receive PCB 108'''''. The optical block 402''' includes openings 513''' and 514''' to receive the receiver 111 and transmitter 110 respectively and



angled slots 1215 to receive the angled transmit PCB 106'''' and the angled receive PCB 108'''''. The angled slots 1215 can provide a friction fit with the angled transmit PCB 106'''' and the angled receive PCB 108'''' or glue or epoxy can be used to couple them together. The angled slots 1215 can also serve to tack the receiver 111 and transmitter 110 in place within the optical block 402''''.

The transmitter 110 couples into the opening 514'''' of the optical block 402'''''. The receiver 111 couples into the opening 513'''' of the optical block 402'''''. They can be held in place by either a friction fit or a glue such as an epoxy.

The transmitter 110 also couples to the transmit PCB 106'''''. The terminals 810 of the transmitter 110 couple to the transmit PCB 106''''' in one embodiment. Using a straddle mount, one or more terminals 810 couple to left edge traces 920L on a left side and one or more terminals 810 couple to right edge traces 920R on a right side of the transmit PCB 106'''''. In an alternate embodiment, the terminals 810 may couple to one side of the transmit PCB 106'''''. In yet another alternate embodiment, the terminals 810 may couple into holes of the transmit PCB 106'''''.

The receiver 111 also couples to the receive PCB 108'''''. The terminals 811 of the receiver 111 couple to the receive PCB 108'''''. Using a straddle mount, one or more terminals 811 couple to left edge traces 921L on a left side and one or more terminals 811 couple to right edge traces 921R on a right side of the receive PCB 108'''''. In an alternate embodiment, the terminals 811 may couple to one side of the receive PCB 108'''''. In yet another alternate embodiment, the terminals 811 may couple into holes of the receive PCB 108'''''.

Referring now to Figure 12B, a rear cross-sectional view

of the assembled fiber optic module 1200 is illustrated. The angled receive PCB 108'''' and the angled transmit PCB 106'''' of the fiber optic module 1200 are angled away from each other with respect to a horizontal or vertical axis thereof. The first terminal pin header 1027T'' is coupled to the angled transmit PCB 1027T'' so that pins 117 are vertical with the reference axis. The second terminal pin header 1027R'' is coupled to the angled receive PCB 108'''' so that pins 113 are vertical with the reference axis. A ground plane 118 can be coupled to a side the angled receive PCB 108'''' or a ground plane 114 can be coupled to a side of the angled transmit PCB 106'''' or both similar to previously described with reference to the vertical boards and Figures 9B-9E. The shield housing or cover 419 couples to the baseplate 805 or 805' around the printed circuit boards. Depending upon the width of the printed circuit boards 106'''' and 108'''' and the width of the fiber optic module 1200, the angles  $\theta_6$  and  $\theta_7$  which the printed boards make with the base or baseplate 805 or 805' can vary between zero and ninety degrees.

While symmetrical angles for the printed circuit boards have been illustrated, combinations can be utilized to form alternate embodiments. For example, one of the printed circuit boards may be arranged on an angle with the base so as to slant while the other printed circuit board may be arranged perpendicular to the base. Figure 16A illustrates a fiber optic module 1600 with such an arrangement for an alternate embodiment of the invention.

Referring now to Figure 13, a receiver optical block 402R and a transmitter optical block 402T are illustrated as an alternative to the optical block 402 or 402'. Previously the fiber optic modules were described and illustrate using a single optical block 402 or 402'. However, the optical blocks

402R and 402T can provide similar functionality to the single optical block 402 or 402'. The receiver optical block 402R couples to the receiver 111 while the transmit optical block 402T couples to the transmitter 110. The receiver 111 and transmitter 110 can be press fit into the openings 513 and 514 or alternatively a glue or epoxy can be inserted into the tacking holes to couple them together. Each optical receiver optical block 402R and transmit optical block 402T provides alignment to an optical fiber and may include a lens. If one more receiver channels are desired, one or more receiver optical blocks 402R can be utilized. If one or more transmit channels are desired, one or more transmit optical blocks 402T can be utilized.

While pins 113 and 117 of the fiber optic modules (100, 400, 800, 900, 1000, 1100, or 1200) facilitate soldering to a host printed circuit board, they can also be plugged into a socket 1402 on a host printed circuit board 1404 as illustrated in Figure 14A. Alternatively, the pins 113 and 117 can each be replaced with one or more sockets 1406R and 1406T coupled to the printed circuit boards on the bottom edge or back edge. In the case of sockets 1406R and 1406T on the bottom edges of the printed circuit boards, the fiber optic module (100, 400, 800, 900, 1000, 1100, or 1200) plugs vertically or downward on sockets 1408R and 1408T for example of the host printed circuit board 1404' as illustrated by Figure 14B. In the case of a socket or sockets 1416R and 1416T on the back edge of the printed circuit boards, the fiber optic module (100, 400, 800, 900, 1000, 1100, or 1200) plugs horizontally or inward into a socket or sockets 1418R and 1418T of the host printed circuit board 1404''.

Referring now Figure 15A, an alternate embodiment of a shielded housing or cover 1519 and an alternate base 1505. The shielded housing or cover 1519 includes a center inner

septum 1515 incorporated as part of the housing or cover to isolate a transmit channel from a receive channel or one channel from another channel. The center inner septum 1515 splits the fiber optic module into a left side and a right side as does the other septums described herein. The housing or cover 1519 further includes a back side 1521, a left side 1522, a right side 1523 and clips or tabs 236. A front side 1524 of the housing or cover 1519 is open to couple to the optical block 402 and/or a nose.

The alternate base 1505 has no septum and may include clip openings or slots 238. Alternately, a base is without the clip openings or slots 238 such that the clips or tabs 236 of the housing or cover are bent over and around the base.

Referring now to Figure 15B, a cross sectional view of a fiber optic module 1000' utilizing the alternate embodiment of the shielded housing or cover 1519 and base 1505 is illustrated. The fiber optic module 1000' is similar to fiber optic module 1000 as described with reference to Figures 10A-10B but for the alternate shielded housing or cover 1519 and the alternate base 1505.

Referring now to Figure 15C, a cross sectional view of the alternate embodiment of the shielded housing or cover 1519 is illustrated. The shielded housing or cover 1519 is a monolithic or integrated shielded housing or cover incorporating the septum 1515. The shielded housing or cover 1519 can be formed of a metal, a plastic or other solid material. The shielded housing or cover 1519 if made of metal, can be formed by forging, stamping or machining. Lower costs methods to fabricate the shielded housing or cover 1519 include injection, transfer, or blow molding the shape out of plastic. The plastic can then be plated, painted or otherwise coated with a conductive material, if conductivity is desired. Likewise a metal part can be overcoated with a non-conductive

material if conductivity is not desired.

Referring now to Figure 15D and Figure 15E, the septum can be angled as well to accommodate parallel angled PCB boards as illustrated by the septum 1515' of the shielded housing or cover 1519' and the septum 1515'' of the shielded housing or cover 1519''.

Referring now to Figure 15F, the septum can be formed separately from the housing or cover and coupled thereto. The shielded housing or cover 1519''' includes a septum 1515''' which is formed separately and coupled together. The septum 1515''' can be coupled to the outer housing by using fusion techniques such as soldering, welding, or melting. Figure 15F illustrates the fuse links 1530 (solder, weld, etc) coupling the septum 1515''' to the outer housing of the shielded housing or cover 1519'''.

Referring now to Figure 15G, the septum can be formed separately from the housing or cover and coupled thereto by alternate means. Figure 15G illustrates the shielded housing or cover 1519'''' including a septum 1515'''' which is formed separately and coupled together. The outer cover of the shielded housing or cover 1519'''' includes a groove 1532 and the septum 1515'''' includes a tongue 1534 to form a tongue and groove system. A glue, adhesive or epoxy 1535 is applied between the tongue and groove system which may be conductive or non-conductive to couple the outer housing and the septum 1515'''' together to form the shielded housing or cover 1519''''.

The fiber optic modules previously described with reference to Figures 8A-15G were illustrated with the optoelectronic devices (transmitter 110 and receiver 111) having its terminals coupled to the printed circuit boards using a straddle mount. However, one or all of the optoelectronic devices may have their terminals coupled to the

printed circuit boards using a through hole mount. In a straddle mount, the optoelectronic device (i.e. the transmitter 110 or the receiver 111) has its optical axis nearly in-line and parallel with a plane of the printed circuit board. In a through hole mount, the optoelectronic device (i.e. the transmitter 110 or the receiver 111) has its optical axis nearly parallel with a plane of the printed circuit board.

Referring now to Figure 16A, a rear cross-section of a fiber optic module 1600 is illustrated having a first optoelectronic device with its terminals coupled to a first printed circuit board in a straddle mount configuration and a second optoelectronic device with its terminals coupled to a second printed circuit board in a through hole mount configuration. Alternatively, both the first optoelectronic device the second optoelectronic device may have their terminals coupled to their respective printed circuit boards in a through hole mount configuration as illustrated by the rear cross-section of fiber optic module 1602 of Figure 16B.

Referring now to Figures 17A-17D, 18A-18B, and 19A-19B additional dual board embodiments of fiber optic modules are illustrated.

Referring now to Figure 17A, fiber optic module 1700 is illustrated. Fiber optic module 1700 includes a vertical board 108V the horizontal board 106H, and an outer housing cover 1719 and a base 1705. The fiber optic modules 1700 may additionally include an optional septum 1715 to shield and separate the electronic circuits on boards 108V and 106H. The board 108V is on one side of the fiber optic module 1700 while the board 106H is on another side of the fiber optic module 1700.

The first printed circuit board 108V has a first optical

electronic device with its terminals coupled near to in a straddle mount configuration. The second printed circuit board 106H has an optical electronic device with its terminals coupled there to in a through hole mount configuration. The base 1705 provides support for the first and second printed circuit boards as well as encloses the fiber optic module 1700. In one embodiment the first printed circuit board 108V is a vertical transceiver printed circuit board while the horizontal printed circuit board 106H is a horizontal transceiver board.

Referring now to Figure 17B, fiber optic module 1702 is illustrated. Fiber optic module 1702 includes a first horizontal printed circuit board 108H, a second vertical printed circuit board 106V, a base 1705 and a cover or housing 1719. Fiber optic module 1702 may also optionally include a septum 1715. Base 1705 is similar to the base 1505 previously described and may include one or more openings in order to allow a connector or a pin or a plurality of pins to pass there through. In one embodiment, the first horizontal printed circuit board 108H is a transmit printed circuit board and the second vertical board 106V is a receive print circuit board. In Figure 17B, the first optical electronic device is coupled to the first horizontal printed circuit board 108H in a through hole mount configuration. The second optical electronic device is coupled to the vertical printed circuit board 106V in a straddle mount configuration.

Referring now to Figure 17C, fiber optic module 1704 illustrated. Fiber optic module 1704 includes housing will cover 1719, a base 1705, a first vertical printed circuit board 108V, and a second slanted printed circuit board 106S. Fiber optic module 1704 may further include septum 1715 to shield electromagnetic radiation from either printed circuit board. The first vertical printed circuit board 108V includes

a first optical electronic device 110 or 111. The second slanted printed circuit board 106S includes a second opto electronic device 110 or 111. In one embodiment the first optic electronic device is coupled to the vertical printed circuit 108V in a straddle mount configuration. In one embodiment the second optic electronic device is coupled to the second slanted printed circuit board 106S in through hole mount configuration.

Referring now to Figure 17D, a fiber optic module 1706 is illustrated. Fiber optic modules 1706 includes a housing or cover 1719, a base 1705, a first slanted printed circuit board 108S, and a second vertical printed circuit board 106V. A first optic electronic device is coupled to the first slanted printed circuit board 108S and a second optic electronic device is coupled to the second vertical printed circuit board 106V. Either the first and/or second optical electronic devices maybe a transmitter or receiver 110 or 111. In one embodiment the first optical electronic device is coupled to the first slanted printed circuit board 108S using a through hole mount configuration. In one embodiment the second optical electronic device 110 or 111 is coupled to the vertical printed circuit board 106V using a straddle mount configuration. The base 1705 may also be referred to as a cover.

Referring now to Figure 18A, a fiber optic module 1800 is illustrated. Fiber optic module 1800 includes a base or cover 1805, a housing or cover 1819, a first vertical printed circuit board 108V-, and a second slanted printed circuit board 106F-. The vertical printed circuit board 108V- includes a ground plane 118. The second slanted printed circuit 106S- includes a ground plane 114. Each of the ground planes provides sufficient shielding.



Referring now to Figure 18B, fiber optic module 1802 is illustrated. Fiber optic module 1802 includes a base or cover 1805, a housing or cover 1819, a first slanted printed circuit board 108S-, and a second vertical printed circuit board 106V-. The first slanted printed circuit board 108S- includes a ground plane 118. The second vertical printed circuit board 106V- includes a ground plane 114. Each of the slanted printed circuit boards in Figures 18A and 18B maybe substituted with a horizontal printed circuit board. In Figures 18A and 18B each of the first and second printed circuit boards included a ground plane. However, it maybe the case that a single ground plane on one of either of the printed circuit boards is sufficient for shielding purposes.

Referring now to Figures 19A-19B, a single printed circuit board includes a ground plane to provide shielding to avoid cross talk between channels. Referring now to Figure 19A, a fiber optic module 1900 is illustrated. Fiber optic module 1900 includes a base or cover 1905, a housing or cover 1919, a first vertical printed circuit board 108V', and a second slanted printed circuit board 106S. In this case, the first vertical printed 108V' includes a ground plane 118 while the second slanted printed circuit board 106S does not.

Referring now to Figure 19B, a fiber optic module 1902 is illustrated. Fiber optic module 1902 includes a base or cover 1905, a housing or cover 1919, a first slanted printed circuit board 108S and a second vertical printed circuit board 106V-.

The second vertical printed circuit board 106V- includes a ground plane 114 while the first slanted printed circuit board 108S does not. In Figures 19A-19B, slanted printed circuit boards 106S and 108S were respectfully described which can also be substituted with a horizontal printed circuit board 106H or horizontal printed circuit board 108H respectfully.

Referring now to Figures 20A-20E, a three-channel system is illustrated which provides a redundant receiver or transmitter channel. Figures 20A-20E illustrate a tri-board embodiments of fiber optic modules to provide a redundant transmit or receive channel. Because of the stress applied to the semiconductor material for the transmitter the more likely the channel to become defective is the transmit channel which includes the emitter. A detector, such as a PIN or PN photodiode commonly used to measure power output in a transmitter, can also be utilized to detect failure of a receiver or a transmitter channel in order to switch to a redundant receiver or transmitter in a fiber optic module. Each receiver in essence would include a redundant photodiode on the same substrate with an extra terminal.

Referring now to Figure 20A, a fiber optic module 2000 is illustrated. Fiber optic module 2000 includes a base or cover 2005, a housing or cover 2019, a first vertical printed circuit board 106V, a second vertical printed circuit board 107V, a third vertical printed circuit board 108V. Each of the vertical printed circuit boards 106V, 107V, and 108V may include a transmitter or receiver optical electronic device 110 or 111. A first optical electronic device is coupled to the vertical printed circuit board 106V using a straddle mount configuration. A second optical electronic device is coupled to the second vertical printed circuit board 107V in a straddle mount configuration. A third optical electronic device is coupled to the third vertical printed circuit board 108V in a straddle mount configuration as well.

Referring now to Figure 20B, a fiber optic module 2002 is illustrated. Fiber optic module 2002 includes a base or cover 2005, a housing or cover 2019, a first vertical printed circuit board 106V, a second horizontal printed circuit board 107H, and a third vertical printed circuit board 108V. The

vertical printed circuit boards 106V and 108V may include a ground plane 114 and 118 respectfully as illustrated in Figure 20B. In one embodiment the vertical printed circuit board 106V has a transmitter or receiver 110 or 111 coupled thereto using a straddle mount configuration. In one embodiment the vertical printed circuit board 108V has a transceiver or receiver 110 or 111 coupled thereto using a straddle mount configuration. In one embodiment the horizontal printed circuit board 107H has a transmitter or receiver 110 or 111 coupled thereto using a through hole mount configuration.

Referring now to Figure 20C, a fiber optic module 2004 is illustrated. A fiber optic module 2004 includes a base or cover 2005, a housing or cover 2019, a first vertical printed circuit board 106V, a second vertical printed circuit board 107V, and a third horizontal printed circuit board 108H. The first vertical printed circuit board 106V has a first optical electronic device 110 or 111 coupled thereto. A second vertical printed circuit board 107V has a second optical electronic device 110 or 111 coupled thereto. The third horizontal vertical printed circuit board 108H includes a third optical electronic device 110 or 111 coupled thereto. In one embodiment the first vertical printed circuit board and the second vertical printed circuit board 106V and 107V have the first and second optical electronic devices coupled thereto using a straddle mount configuration. In one embodiment the horizontal printed circuit board 108H includes a third optical device coupled thereto using a through hole mount configuration.

Referring now to Figure 20D, a fiber optic module 2006 is illustrated. A fiber optic module 2006 includes a base of cover 2005, a housing or cover 2019, a first vertical printed circuit board 106H, a second vertical printed circuit board 107V, and a third horizontal printed circuit board 108V. The

first vertical printed circuit board 106H includes a first optical electronic coupled thereto. The second vertical printed circuit board 107V includes a second optical electronic device coupled thereto. The third vertical printed circuit board 108V includes a third optical electronic device coupled thereto. In any of the first, second, or third optical electronic devices can be a transmitter 110 or a receiver 111. In one embodiment the horizontal printed circuit board 106H includes transmitter or receiver coupled thereto using a through-hole mount configuration. The second and third vertical printed circuit boards 107V and 108V include a transmitter or receiver coupled thereto using a straddle mount configuration. In each of the cases Figures 20A-20D, the vertical printed circuit boards are parallel to each other in parallel to the optical axis of the transmitter or receiver.

Referring now to Figure 20E, the fiber optic module 2008 is illustrated. Fiber optic module 2008 includes a first horizontal printed circuit board 106H, a second vertical printed circuit board 107V, a third horizontal printed circuit board 108H, a base 2005, and a housing or cover 2019. The first horizontal printed circuit board 106H includes a first optical electronic device coupled thereto. The second vertical printed circuit board 107V includes a second optical electronic device coupled thereto. The third horizontal printed circuit board 108H includes a third optical electronic device coupled thereto. The first, second, and third can be a transmitter 110 or a receiver 111. In one embodiment the first optical electronic device is coupled to the printed circuit board 106H in a through hole mount configuration. In one embodiment the second optical electronic device is coupled to the second vertical printed circuit board 107V in a straddle mount configuration. In one embodiment the third

optical electronic device is coupled to the third horizontal printed circuit board 108H using a through hole mount configuration.

Referring now to Figure 20F, the fiber optic module 2010 is illustrated. Fiber optic module 2010 includes a first horizontal printed circuit board 106H, a second horizontal printed circuit board 107H, a third horizontal printed circuit board 108H, a base or cover 2005, and a housing or cover 2019. The first horizontal printed circuit board 106H includes a first optical electronic device coupled thereto. The second horizontal printed circuit board 107H includes a second optical electronic device coupled thereto. The third horizontal printed circuit board 108H includes a third optical electronic device coupled thereto. The first, second, and third optoelectronic devices can be either a transmitter 110 or a receiver 111. In one embodiment the first optical electronic device is coupled to the printed circuit board 106H in a through hole mount configuration. In one embodiment the second optical electronic device is coupled to the second horizontal printed circuit board 107H in a through hole mount configuration. In one embodiment the third optical electronic device is coupled to the third horizontal printed circuit board 108H using a through hole mount configuration.

In each of the fiber optic modules illustrated in Figures 20A-20F, the base or cover 2005 and the housing or cover 2019 may provide shielding by being conductive and formed of a conductive material. In the fiber optic modules illustrated in Figures 20A-20F, the printed circuit boards may include pins or connectors coupled thereto in order to make electrical connection to a connector or through holes within a host printed circuit board of a system.

Referring now to Figures 21A-21H, a four channel or

double redundant fiber optic modules are illustrated. Figures 21A-21H illustrate a quad-board embodiment of fiber optic modules. In one case, a redundant transceiver and a redundant receiver for a transceiver fiber optic module can be provided.

Alternatively each channel can be provided with redundancy.

In another case, a four channel receiver/transceiver or transmitter is provided which can be used to provide four full time communication channels. In another case, a dual redundant system for a transmit channel or a receive channel.

Referring now to Figure 21A, fiber optic module 2100 is illustrated. Fiber optic 2100 includes a base or cover 2105, a housing or cover 2119, a first vertical printed circuit board 105V, a second vertical printed circuit board 106V, a third vertical printed circuit board 107V, and a fourth vertical printed circuit board 108V. Each of the first, second, third, and fourth vertical printed circuit boards may include a transmitter 110 or a receiver 111. In one embodiment each of the first, second, third, and fourth optical electronic devices coupled to the first, second, third and fourth vertical printed circuit boards respectfully may be coupled thereto using a straddle mount configuration. The base 2105 and/or the housing 2119 maybe conductive in order to shield electromagnetic radiation.

Referring now to Figure 21B, a fiber optic module 2102 is illustrated. Fiber optic module 2102 includes a first horizontal printed circuit board 105H, a second vertical printed circuit board 106V, a third vertical printed circuit board 107V and a fourth horizontal printed circuit board 108H.

Each of the first, second, third, and fourth printed circuit boards include a first, second, third, and fourth optical electronic devices coupled thereto. The first, second, third, and fourth optical electronic devices maybe a transmitter 110 or a receiver 111. In one embodiment the first and fourth

optical electronic devices are coupled to the first and fourth horizontal printed circuit boards using a through hole mount configuration. The second and third optical electronic devices are coupled to the second and third vertical printed circuit boards 106V and 107V respectfully using a straddle mount configuration.

Referring now to Figure 21C, a fiber optic module 2104 is illustrated. Fiber optic module 2104 includes a first vertical printed circuit board 105V, a second horizontal printed circuit board 206H-, and third vertical printed circuit 108V, a base 2105, a housing or cover 2119. The first vertical printed circuit board 105V includes a first optical electronic device coupled thereto. The second horizontal printed circuit board 106H- includes a second and third optical electronic device coupled thereto. The third vertical printed circuit board 108V includes a fourth optical electronic device coupled thereto. In one embodiment the first and fourth optical electronic devices are coupled to respective vertical printed circuit boards 105V and 108V using a straddle mount configuration. In one embodiment the second and third optical electronic devices are coupled to the second horizontal printed circuit board 106H- using a through hole mount configuration. Additionally, the vertical printed circuit boards 105V or 108V may include a ground plane 114 or ground plane 116 respectfully.

Referring now to Figure 21D, a fiber optic module 2106 is illustrated. Fiber optic module 2106 includes a first vertical printed circuit board 105V, a second horizontal printed circuit board 106H, a third horizontal printed circuit board 107H, a fourth vertical printed circuit board 108V, a base or cover 2105, and a housing or cover 2119. The first vertical printed circuit board 105V has a first optical electronic device coupled thereto. The second horizontal

printed circuit board has a second optical electronic device thereto. The third horizontal printed circuit board 107H has third optical electronic device coupled thereto. The fourth vertical circuit board 108V includes a fourth optical electronic device coupled thereto. In one embodiment the first and fourth optical electronic devices are coupled to the vertical printed circuit boards 105V and 108V respectfully using a straddle mount configuration. In one embodiment the second and third optical electronic devices are coupled to the second and third horizontal printed circuit boards respectfully using a through hole mount configuration.

Referring now to Figure 21E, a fiber optic module 2108 is illustrated. Fiber optic module 2108 includes a first vertical printed circuit board 105V, a second horizontal printed circuit 106H, a third vertical printed circuit board 107V and a fourth horizontal printed circuit board 108H, base or cover 2105, and housing or cover 2119. The first, second, third, and fourth printed circuit boards include a first, second, third, and fourth optical electronic devices coupled thereto respectfully. In one embodiment the first and third optical electronic devices coupled respectfully to the first vertical printed circuit board and third vertical printed circuit using straddle mount configuration. In one embodiment the second and fourth optical electronic device couple respectively to the second horizontal printed circuit board and fourth horizontal printed circuit board using a through hole mount configuration. The first, second, third, and fourth optical electronic devices maybe a receiver or a transmitter optical electronic device.

Referring now to Figure 21F, a fiber optic module 2110 is illustrated. Fiber optic module 2110 includes a first vertical printed circuit board 105V, a second vertical printed circuit board 106V, a third vertical printed circuit board



107V, a fourth horizontal printed circuit board 108H, a base or cover 2105, and a housing or cover 2119. In this case three printed circuit boards are vertical and parallel to one another. A first, second, third, and fourth optical electronic devices are coupled respectively to the first, second, third, and fourth printed circuit boards. In one embodiment the first optical electronic device, second optical electronic device, and third optical electronic device are coupled to the first vertical printed circuit board 105V, the second 106V and the third vertical circuit board 107V using a straddle mount configuration. In one embodiment the fourth optical electronic device is coupled to the four horizontal printed circuit boards 108H using a through hole mount configuration. The first, second, third, and fourth optical electronic devices maybe a receiver or transmitter 110 or 111.

Referring now to 21G, the fiber optic module 2112 is illustrated. The fiber optic module 2112 includes a first vertical printed circuit board 105V, a second vertical printed circuit board 106V, a third horizontal printed circuit board 108H, a base or cover 2105, and a housing or cover 2119. The first and second printed circuit boards are vertical printed circuit boards parallel with one another and the optical axes of the first and second optical electronic devices coupled thereto. The third horizontal printed circuit board 108H includes a third and fourth optical electronic devices coupled thereto. In one embodiment the first and second optical electronic devices are coupled respectively to the first vertical printed circuit board 105V and the second vertical printed circuit board 106V using a straddle mount configuration. In one embodiment the third and fourth optical electronic devices are coupled to the third horizontal printed circuit board 108H- using a through hole mount configuration.

Referring now to Figure 21H, the fiber optic module 2114

is illustrated. Fiber optic module 2114 includes a first horizontal printed circuit board 105H, a second horizontal printed circuit board 106H, a third vertical printed circuit board 107V, a fourth vertical printed circuit board 108V, a base or cover 2105, and a housing or cover 2119. The third and fourth vertical printed circuit boards 107V and 108V are parallel to one another and the optical axes of the third and fourth optical electronic devices. The first printed circuit board and second printed circuit board include a first optical electronic devices coupled respectively thereto. In one embodiment the first and second optical electronic devices are coupled respectively to the horizontal printed circuit board 105H and 106H using a through hole mount configuration. In one embodiment the third and fourth optical electronic devices are respectively coupled to the third and fourth vertical printed circuit boards 107V and 108V respectively using a straddle mount configuration.

In each of the fiber optic modules illustrated in Figures 21A-21H, the printed circuit boards may respectively include pins or electronically connectors in order to make connection to a host printed circuit board of a system. In each of the fiber optic modules illustrated in 21A-21H at least two vertical printed circuit boards are included in parallel together. In this manner, either four channels can be utilized or a redundancy for each channel maybe provided. In each of the fiber optic modules 2100-2114 illustrated in Figures 21A-21H, one or more of the printed circuit boards may include ground planes to reduce cross talk and reduce electromagnetic interference. Additionally, combinations of three horizontal printed circuit boards and one vertical printed circuit board can form alternate embodiments of fiber optic modules as well as four horizontal printed circuit boards can form alternate embodiments of four channel fiber

optic modules that can provide four channels or dual redundancy.

While previous embodiments of fiber optic modules have been described as pluggable, solderable or embedded utilizing pins or electrical connections, a miniature back plane can be introduced into fiber optic modules in order to allow an individual fiber optic channel and the associated printed circuit board to be replaced.

Referring now to Figures 22A, 22B and 22C, a horizontal array of fiber optic channels is illustrated in a fiber optic module including a miniature back plane.

Referring now to Figure 22A, fiber optic module 2200 is illustrated. The fiber optic module 2200 includes a plurality of n vertical printed circuit boards 106aV' and/or 108aV' through 106nV' and/or 108nV', a miniature back plane 2212, an optical block 2202, a housing 2219, and a base recover 2205. The plurality of vertical printed circuit boards 106aV' and/or 108aV' through 106nV' and/or 108nV' include an opto-electronic device 110 or 111 coupled thereto and an edge connector 2230.

Each of the edge connectors 2230 of the vertical printed circuit boards couple into an edge connector 2214 of the miniature back plane 2212. The miniature back plane 2212 includes pins or an electrical connector 2218 for coupling to a host printed circuit board of a system. The one or more vertical printed circuit boards are arranged in a horizontal array with respect to the system printed circuit board. The optical block 2202 includes open ends to receive the opto electronic devices of the vertical printed circuit boards and a plurality of lenses 421 or 423 lined with the optical axes of the plurality of opto electronic devices and open ends 2203 to mate with optical fiber connectors.

Referring now to Figure 22B, the top view of the fiber

optic module 2200 is illustrated. The plurality of opto-electronic devices 110 or 111 coupled to each respective printer circuit board using a straddle mount configuration in one embodiment. The back plane 2212 includes a plurality of female edge connectors 2214 or male edge connectors 2214 as the case may be to interface to the edge connector of the plurality of printed circuit boards 106 and/or 108. The miniature back plane 2212 includes traces or busses to couple between the edge connectors 2214 and the pins or electrical connector 2218. Fiber optic module 2200 provides support for two or more channels. The one or more vertical boards 106aV' and/or 108aV' through 106nV' and/or 108nV' can be slid in and out of the fiber optic module 2200 to replace them as necessary by decoupling them from the miniature back plane 2212. The base 2205 provides support through a slot of through other means described previously.

The optical block 2202 may be a single optical block 2202 in order to access the plurality of printed circuit boards 106 or 108 at a time or may be individual optical blocks for each respective printed circuit board. In the fiber optic module 2200, each of the printed circuit boards 106 or 108 are vertical printed circuit boards in parallel with each other and the optical axes of the respective optoelectronic electronic device. The printed circuit boards may alternatively be slanted at an angle with respect to the printed circuit board 2250 in parallel with each other and in parallel with the optical axes of the respective opto-electric device. Optionally, each channel may be horizontal with respect to the system or host printed circuit board such that a plurality of horizontal printed circuit boards are provided.

However, the horizontal configuration of the printed circuit boards are expected to use additional horizontal space.

Referring now to Figure 22C, the front view of the fiber

optic module 2200 is illustrated. Fiber optic module 2200 is a horizontal array of fiber optic channels with respect to the host parent circuit board 2250 of a system.

Referring now to Figures 23A and 23B, a magnified view of sides of the printed circuit board 106 through 108 and the edge connectors 2214 or 2414 and the miniature back plane are illustrated. Figures 23A-23C illustrate how the printed circuit boards 106 and 108 coupled to the back plane. The edge connector 2230 of the printed circuit board 106 or 108 includes one or more pads 2300A on one side and one or more pads 2300B on another side of the printed circuit board. The edge connector 2214 or 2414 of the back plane 2212 or 2412 include a plurality of pins 2302A on one side, a plurality of pins 2302B on another side.

Referring now to Figure 23C, the pads 2300A and 2300B are on opposite sides of the edge connector 2230 of the printed circuit board 106 or 108 is more clearly illustrated. The pins 2302A and 2302B of the edge connector 2214 or 2414 are also illustrated more clearly in Figure 23C. The edge connector 2214 or 2414 includes pins 2304A and 2304B coupled to traces of the miniature back plane 2212 or 2412. A number of the pads 2300A and/or 2300B can be staggered in order that ground may be provided first and power may be provided prior to make connections for signal lines. In this case the printed circuit boards 106 or 108 may be hot-pluggable into the back plane 2212 or 2412. In this manner, power can be maintained to the other fiber optic channels while a single channel is replaced.

Figures 24A-24J illustrate horizontal arrays of fiber optic channels for a fiber optic module.

Referring now to Figure 24A, fiber optic module 2400 is illustrated. Fiber optic module 2400 is a vertical array of

fiber optic channels with respect to the host printed circuit board 2250.

Referring now to Figure 24B, the fiber optic module 2400 includes an optical block 2402, a plurality of horizontal print circuit boards 106aH' or 108aH' through 106nH' or 108nH', a miniature back plane 2412, a housing or cover 2419, and a base or cover 2405. The plurality of horizontal printed circuit boards includes a plurality of opto-electronic devices coupled thereto. The miniature back plane 2412 includes a plurality of edge connectors 2414 for coupling to the edge connectors 2230 of the horizontal printed circuit boards. The optical block 2402 includes a plurality of lenses 421 or 423, openings for the receipt of the opto-electronic devices 110 and 111, and openings 2403 to receive fiber optic connector.

Back plane 2412 further includes pins or an electrical connector 2418 for coupling to the host printed circuit board 2250.

Referring now to Figure 24C, a rear cross-sectional view of the fiber optic module 2400 is illustrated. The plurality of horizontal printed circuit boards 106H or 108H are horizontal with respect to the host printed circuit board 2250 and in parallel with each other and in line and in parallel with the optical axes of the opto-electronic devices. Referring now to Figures 24D-24J, alternate embodiments of the vertical array of fiber optic channels is illustrated.

Referring to Figure 24D, the plurality of printed circuit boards are now slanted such that slanted printed circuit boards 106S or 108S are in each respective channel and slanted with respect to the host printed circuit board 2250. Each of the respective embodiments 24D-24J of fiber optic modules includes the components illustrated in 24B including the optical block 2402 and the miniature back plane 2412 but for

the angle of the edge connectors 2414 with respect to the angle of the printed circuit boards and the respective edge connectors 2230.

Referring to Figure 24E, fiber optic module 2454 is illustrated incorporating one or more horizontal printed circuit boards 106H or 108H and one or more slanted printed circuit boards 106S or 108S with respect to the host printed circuit board 2250.

Referring now to Figure 24F, a plurality of horizontal printed circuit board 106H' or 108H' are illustrated with the respective opto-electronic devices coupled thereto using a straddle mount configuration. Referring back to Figure 24C, the horizontal printed circuit boards 106H or 108H have the respective opto-electronic devices coupled thereto using a straddle-mount configuration.

Referring now to Figure 24G, a plurality of printed circuit boards using a mixture of straddle mount and through hole mount configurations are illustrated including horizontal printed circuit boards 106H or 106H' or slanted printed circuit boards 106S or 106S' or 108S' or 108S or 108H or 108H'.

Referring now to Figure 24H, a plurality of vertical printed circuit boards using straddle mount or through hole mount configurations are illustrated. The plurality of printed circuit boards illustrated in Figure 24H may be vertical printed circuit boards 106V or 106V' or 108V or 108V' for respective transmit or receive printed circuit boards in a straddle mount or through hole mount configuration.

Referring now to Figure 24I, fiber optic module 2462 is illustrated. Fiber optic module 2462 includes a plurality of printed circuit boards in a horizontal, vertical or slanted

configuration. Fiber optic module 2462 may include horizontal, vertical or slanted receiver printed circuit boards 106H, 106V, 106S respectively and/or one or more transmit printed circuit boards horizontal, vertical or slanted 108H, 108V, or 108S respectively.

Referring now to Figure 24J, fiber optic module 2464 is illustrated including a mixture of horizontal and vertical of printed circuit boards. Printed circuit boards may be horizontal or vertical transmit boards 106H, or 106V and/or horizontal or vertical receive printed circuit boards 108H or 108V. While Figures 24A-24J illustrate a vertical array of fiber optic channels, a horizontal array and a vertical array may be combined together.

Figures 25A-25I illustrate a 2x2 array of fiber optic channels for fiber optic module.

Referring now to Figure 25A, the fiber optic module 2500 is illustrated having a two-by-two array of fiber optic channels with respect to the host printed circuit board 2250.

Referring now to Figure 25B, the fiber optic module 2500 includes an optical block 2502, the plurality of printed circuit boards 106 or 108, the miniature back plane 2212 or 2412, the housing 2519 and a base 2505. The plurality of printed circuit boards 106 or 108 may be slanted printed circuit boards 106S or 108S or horizontal printed circuit boards 106H or 108H or vertical printed circuit boards 106V or 108V for transmit and receive respectively. Each of the respective printed circuit boards 106 or 108 include an edge connector 2230 for coupling into the edge connectors 2214 or 2414 of the miniature back plane 2212 or 2412 respectively. The miniature back plane 2212 or 2412 further includes pins or an electrical connector 2218 or 2418 for coupling to the host printed circuit board 2250. The edge connectors 2214 or 2414



are arranged in the two-by-two array associated with the configuration of the printed circuit boards 106 or 108 in a slanted, horizontal or vertical configuration.

In Figure 25C, the fiber optic module 2500 includes horizontal printed circuit boards 106aH - 106dH and/or horizontal printed circuit boards 108aH - 108dH. In Figure 25D, the printed circuit boards 106, 108 are illustrated in a horizontal configuration.

Referring now to Figures 25D - 25I, alternate configurations of the printed circuit boards are in a two-by-two array as illustrated. In Figure 25D, fiber optic module 2552 is illustrated. Fiber optic module 2552 includes a two-by-two array of vertical printed circuit boards 106aV - 106dV and/or 108aV - 108dV with respect to the first printed circuit board 2250. Fiber optic modules illustrated in Figures 25D - 25I include components illustrated in Figure 25A - 25C but for the orientation of the printed circuit boards and the edge connectors 2214 or 2414.

Referring now to Figure 25E, a fiber optic module 2554 is illustrated. Fiber optic module 2554 includes a plurality of slanted printed circuit boards including receiver printed circuit boards 106aS - 106dS and/or transmit printed circuit boards 108aS - 108dS with respect to the host printed circuit board 2250.

Referring now to Figure 25F, fiber optic module 2556 is illustrated. Fiber optic module 2556 includes a plurality of slanted printed circuit boards including receiver printed circuit boards 106aS' - 106dS' and/or transmit printed circuit boards 108aS' - 108dS'. Each of the printed circuit boards illustrated in Figures 25D-25I include an opto-electronic device coupled thereto in either a straddle mount configuration and/or a through hole mount configuration.

Additionally, the two-by-two array of printed circuit boards may include the ground plane 114 or 116 coupled respectively thereto to shield in reduced cross channel or cross talk interference. In Figure 25F, the printed circuit boards are slanted in such a way that the back sides may include ground planes to shield cross-talk or cross-channel interference.

Referring now to Figure 25G, a pair of printed circuit boards are vertical and parallel with each other with respect to the cross printed circuit board 2250 and their respective optical axes of the opto-electronic devices. Another pair of printed circuit boards are horizontal and parallel with respect to each other and with respect to the host printed circuit board 2250. The host printed circuit boards 106aV or 108aV and 106cV or 108cV are the vertical printed circuit boards. The printed circuit boards 106bH or 108bH and 106dH or 108dH are the horizontal printed circuit boards.

Referring now to Figure 25H, fiber optic module 2560 is illustrated. The fiber optic module 2560 includes a pair of vertical printed circuit boards 106aV' or 108aV' and 106cV' or 108cV' including opto-electronic devices mounted thereto in a through-hole configuration. Fiber optic module 2560 further includes horizontal printed circuit boards 106bH' or 108bH' and 106dH' or 108dH' with opto-electronic devices coupled thereto in straddle mount configuration.

Referring now to Figure 25I, fiber optic module 2562 is illustrated. Fiber optic module 2562 includes a pair of horizontal printed circuit boards 106AH' or 108AH' and 106cH' or 108cH'. Fiber optic module 2562 further includes vertical printed circuit boards 106bV' or 108bV' and 106dV' or 108dV' including opto-electronic devices coupled thereto in a through hole mount configuration.

While a two-by-two array of fiber optic channels was

illustrated within the fiber optic modules illustrated in Figures 25A-25I, an n-by-n array of fiber optic channels may be incorporated into a fiber optic module.

Figures 26A-26B, 27A-27B, 28, and 29 illustrate n-by-n arrays of fiber optic channels for fiber optic modules.

Referring now to Figure 26A and 26B, an n-by-n array of fiber optic channels is illustrated in a fiber optic module 2600. The fiber optic module 2600 includes n-by-n vertical printed circuit boards 106(a,a)V or 108(a,a)V through 106(n,n)V or 108(n,n)V. Fiber optic module 2600 includes a plurality of n-by-n vertical printed circuit boards 106V or 108V. Each of the plurality of n-by-n vertical printed circuit boards 106V or 108V are respectively in parallel with one another and the optical axes of the respective opto-electronic devices coupled thereto. The opto-electronic device may be straddle mount mounted as shown in Figure 2600 or may be through hole mounted as shown and described in previous Figures.

Referring now to Figure 26B, a cross-sectional side view of the fiber optic module 2600 is illustrated. Fiber optic module 2600 includes a housing or cover 2619, a base or cover 2605, an optical block 2602, a miniature back plane 2612 and a plurality of vertical printed circuit boards 106V or 108V for the respective receive or transmit channel. The optical block 2602 may be separated into individual rows or individual optical blocks for each respective fiber optic channel. In one embodiment the optical block is in the form of a plurality of rays of optical blocks 2602Ra - 2602Rn. Each of the rows including the plurality of lenses 421 and 423 align with the optical axes of the respective receive 110 or transmitter 111 of the opto-electronic device. The plurality of vertical printed circuit boards includes an edge connector 2230

coupling into edge connectors 2614 of the back plane 2612. The edge connectors 2614 and edge connection of the printed circuit boards 2230 are similar to the edge connectors previously described with reference to Figures 23A - 23C. The back plane 2612 further includes pins and an electrical connector 2318 or 2418 for coupling to the host printed circuit board 2250. The optical blocks 2602 further include openings to receive the opto-electronic devices of each respective printed circuit board and may include a slot to align and couple with the edge of the printed circuit boards.

Referring now to Figure 27A, an alternate embodiment of the n-by-n fiber optic module is illustrated. In Figure 27A fiber optic module 2700 is illustrated including an n-by-n array of horizontal printed circuit boards and their respective opto-electronic devices coupled thereto. The horizontal printed circuit boards may be receiver or transmit boards 106(a,a)H or 108(a,a)H through 106(n,n)H or 108(n,n)H.

Referring now to Figure 27B, a cross-sectional side view of the fiber optic module 2700 is illustrated. Fiber optic module 2700 includes an optical block 2702, a plurality of printed circuit boards 106H or 108H arrayed in an n-by-n array, a miniature back plane 2712, a housing 2719 and a base 2705. The optical block 2702 may be arranged into a plurality of rows of optical blocks including rays 2702Ra - 27Rn. Each of the rows including a plurality of lenses 421 or 423 for coupling respectively to the optical axis of the opto-electronic devices. Each of the plurality of horizontal printed circuit boards includes an opto-electronic device coupled thereto at one end and a nudge connector at the other end. Each of the edge connectors 2230 of the respective printed circuit boards couples to the edge connector 2214 or 2414 of the back plane 2712. The back plane 2712 includes a plurality of edge connectors 2214 or 2414, a plurality of

traces coupled thereto for coupling between the edge connectors 2414 and pins or electrical connector 2218 or 2418.

The pins or electrical connector 2218 or 2418 are coupled to openings or a connector of the host printed circuit board 2250.

Referring now to Figure 28, an alternate embodiment of the n-by-n array of fiber optic channels is illustrated by the fiber optic module 2800. The fiber optic module 2800 includes an n-by-n array of slanted printed circuit boards 106(a,a)S' or 108(a,a)S' through 106(n,n)S' or 108(n,n)S'. Each of the plurality of slanted printed circuit boards includes an opto-electronic device 110 or 111 coupled thereto in a through hole mount configuration. The plurality of printed circuit boards are slanted with respect to the host printed circuit board 2250 as illustrated in Figure 28.

Referring now to Figure 29, an alternate embodiment of an n-by-n array of fiber optic channels for a fiber optic module are illustrated. In Figure 29, fiber optic module 2900 is illustrated including an n-by-n array of slanted printed circuit boards. The n-by-n array of slanted printed circuit boards include opto-electronic devices coupled thereto using a straddle mount configuration. Fiber optic module 2900 includes slanted printed circuit boards 106(a,a)S or 108(a,a)S through 106(n,n)S or 108(n,n)S for the respective receive or transmit printed circuit boards. In this manner, an n-by-n array of fiber optic channels can be supported within a fiber optic module. In the alternate embodiments of the n-by-n array, the fiber optic modules include elements illustrated in Figures 26B and 27B but for the angle and orientation of the printed circuit boards and the edge connectors 2214 or 2414.

Referring now to Figure 30, fiber optic module 3000 is illustrated. Fiber optic module 3000 includes two vertical

printed circuit boards and a horizontal printed circuit board without a base. Fiber optic module 3000 includes a cover or housing 3019, a vertical printed circuit board 106V, a vertical printed circuit board 108V, and a horizontal printed circuit board 107H. A horizontal printed circuit board 107H acts similar to a base plate providing support for the vertical printed circuit boards 106V and 108V. The horizontal printed circuit board 107H includes pins 113 and 117 to couple to a host printed circuit board. The vertical printed circuit boards 106V and 108V couple electrically to the horizontal printed circuit board 107H similarly to that previously described when connecting one printed circuit board to another. The vertical printed circuit board 106V includes a first optic electronic device 110 or 111 coupled thereto. The vertical printed circuit board 108V includes a second optic electronic device 110 or 111 coupled thereto. In one embodiment in the first and second optical electronic devices are coupled to the respective vertical printed circuit boards using a straddle mount configuration. The cover or housing 3019 maybe formed of a metal or connector material in order to shield the electronics of the printed circuit boards of electro magnetic interference. The cover or housing 3019 couples to the horizontal printed circuit board 107H.

Referring now to Figure 31, fiber optic module 3100 is illustrated. Fiber optic module 3100 includes two vertical printed circuit boards with a horizontal printed circuit board and a base plate or base. Fiber optic module 3100 includes a cover or housing 3019, a base 3105, a vertical printed circuit board 106V, a vertical printed circuit board 108V, and a horizontal printed circuit board 107H. The vertical printed circuit board 106V and 108V couple electrically to the horizontal printed circuit board 107H. The horizontal printed circuit 107H pins 113 and 117 protruded through openings in

the base 3105. The first vertical printed circuit board 106V includes a first optic electronic device 110 or 111 coupled thereto. The second vertical printed circuit board 108V includes a second optic electronic device 110 or 111 coupled thereto. In one embodiment the optic electronic devices are coupled to the vertical printed circuit boards using a straddle mount configuration. The cover or housing 3119 couples to the base 3105.

Referring now to Figure 32, fiber optic module 3200 is illustrated. Fiber optic module 3200 includes one vertical printed circuit board and one horizontal printed circuit board without a base plate or base. Fiber optic module 3200 includes a cover or housing 3019, a vertical printed circuit board 106V, and a horizontal printed circuit board 108H. The vertical printed circuit board 106V includes a first optic electronic device 110 or 111 coupled thereto. A horizontal printed circuit board 108H includes a second optic electronic device 110 or 111 coupled thereto. A horizontal printed circuit board 108H includes pins 113 and 117 coupled to a host printed circuit board. In one embodiment the first optic electronic device is couple to the vertical printed circuit board 106V using a straddle mount configuration. In one embodiment the second optic electronic device is coupled to the horizontal printed circuit board 108H using a through hole mount configuration. The vertical printed circuit board 106V couples to the horizontal printed circuit board 108H or signals to pass between the pins and the vertical printed circuit board 106V. The cover or housing 3219 couples to the horizontal printed circuit board 108H.

Referring now to Figure 33, fiber optic module 3300 is illustrated. Fiber optic module 3300 includes one vertical printed circuit, one horizontal printed circuit board and a base plate. Fiber optic module 3300 includes a base 3305, a

cover or housing 3319, a vertical printed circuit board 106V, and a horizontal printed circuit board 108H. The vertical printed circuit 106V includes a first optic electronic device 110 or 111 coupled thereto. The horizontal printed circuit board 108H includes a second optic electronic device 110 or 111 coupled thereto. The horizontal printed circuit board includes pins 113 and 117 protruding through openings in the base 3305. The cover or housing 3319 couples to the base 3305.

The vertical printed boards in Figures 30-33 couple to the horizontal printed circuit board using an electrical connection such as solder joints 917R or 917T previously described herein with reference to Figures 9A and 9B or pin headers 1027R and 1027T previously described with reference to Figures 10A-10B. The solder joints or pin headers can be on one side or both sides of the vertical printed circuit board coupling to the horizontal printed circuit board.

The previous detailed description describes fiber optic modules as including a receiver and transmitter. However, one of ordinary skill can see that a fiber optic module may be a receiver only or a transmitter only such that only one board type is used. Additionally, the previous detailed description described one receive channel and one transmit channel. However, the invention may be extended to a plurality of channels in parallel which can be all transmit channels, all receive channels or both receive and transmit channels into multiple fiber optic cables.

As those of ordinary skill will recognize, the invention has a number of advantages over the prior art.

The preferred embodiments of the invention are thus described. While the invention has been described in particular embodiments, the invention should not be construed



as limited by such embodiments, but rather construed according to the claims that follow below.

11  
12  
13  
14  
15  
16  
17  
18  
19  
20  
21  
22  
23  
24  
25  
26  
27  
28  
29  
30  
31  
32  
33  
34  
35  
36  
37  
38  
39  
40  
41  
42  
43  
44  
45  
46  
47  
48  
49  
50  
51  
52  
53  
54  
55  
56  
57  
58  
59  
60  
61  
62  
63  
64  
65  
66  
67  
68  
69  
70  
71  
72  
73  
74  
75  
76  
77  
78  
79  
80  
81  
82  
83  
84  
85  
86  
87  
88  
89  
90  
91  
92  
93  
94  
95  
96  
97  
98  
99  
100  
101  
102  
103  
104  
105  
106  
107  
108  
109  
110  
111  
112  
113  
114  
115  
116  
117  
118  
119  
120  
121  
122  
123  
124  
125  
126  
127  
128  
129  
130  
131  
132  
133  
134  
135  
136  
137  
138  
139  
140  
141  
142  
143  
144  
145  
146  
147  
148  
149  
150  
151  
152  
153  
154  
155  
156  
157  
158  
159  
160  
161  
162  
163  
164  
165  
166  
167  
168  
169  
170  
171  
172  
173  
174  
175  
176  
177  
178  
179  
180  
181  
182  
183  
184  
185  
186  
187  
188  
189  
190  
191  
192  
193  
194  
195  
196  
197  
198  
199  
200  
201  
202  
203  
204  
205  
206  
207  
208  
209  
210  
211  
212  
213  
214  
215  
216  
217  
218  
219  
220  
221  
222  
223  
224  
225  
226  
227  
228  
229  
230  
231  
232  
233  
234  
235  
236  
237  
238  
239  
240  
241  
242  
243  
244  
245  
246  
247  
248  
249  
250  
251  
252  
253  
254  
255  
256  
257  
258  
259  
260  
261  
262  
263  
264  
265  
266  
267  
268  
269  
270  
271  
272  
273  
274  
275  
276  
277  
278  
279  
280  
281  
282  
283  
284  
285  
286  
287  
288  
289  
290  
291  
292  
293  
294  
295  
296  
297  
298  
299  
300  
301  
302  
303  
304  
305  
306  
307  
308  
309  
310  
311  
312  
313  
314  
315  
316  
317  
318  
319  
320  
321  
322  
323  
324  
325  
326  
327  
328  
329  
330  
331  
332  
333  
334  
335  
336  
337  
338  
339  
340  
341  
342  
343  
344  
345  
346  
347  
348  
349  
350  
351  
352  
353  
354  
355  
356  
357  
358  
359  
360  
361  
362  
363  
364  
365  
366  
367  
368  
369  
370  
371  
372  
373  
374  
375  
376  
377  
378  
379  
380  
381  
382  
383  
384  
385  
386  
387  
388  
389  
390  
391  
392  
393  
394  
395  
396  
397  
398  
399  
400  
401  
402  
403  
404  
405  
406  
407  
408  
409  
410  
411  
412  
413  
414  
415  
416  
417  
418  
419  
420  
421  
422  
423  
424  
425  
426  
427  
428  
429  
430  
431  
432  
433  
434  
435  
436  
437  
438  
439  
440  
441  
442  
443  
444  
445  
446  
447  
448  
449  
450  
451  
452  
453  
454  
455  
456  
457  
458  
459  
460  
461  
462  
463  
464  
465  
466  
467  
468  
469  
470  
471  
472  
473  
474  
475  
476  
477  
478  
479  
480  
481  
482  
483  
484  
485  
486  
487  
488  
489  
490  
491  
492  
493  
494  
495  
496  
497  
498  
499  
500  
501  
502  
503  
504  
505  
506  
507  
508  
509  
510  
511  
512  
513  
514  
515  
516  
517  
518  
519  
520  
521  
522  
523  
524  
525  
526  
527  
528  
529  
530  
531  
532  
533  
534  
535  
536  
537  
538  
539  
540  
541  
542  
543  
544  
545  
546  
547  
548  
549  
550  
551  
552  
553  
554  
555  
556  
557  
558  
559  
560  
561  
562  
563  
564  
565  
566  
567  
568  
569  
570  
571  
572  
573  
574  
575  
576  
577  
578  
579  
580  
581  
582  
583  
584  
585  
586  
587  
588  
589  
590  
591  
592  
593  
594  
595  
596  
597  
598  
599  
600  
601  
602  
603  
604  
605  
606  
607  
608  
609  
610  
611  
612  
613  
614  
615  
616  
617  
618  
619  
620  
621  
622  
623  
624  
625  
626  
627  
628  
629  
630  
631  
632  
633  
634  
635  
636  
637  
638  
639  
640  
641  
642  
643  
644  
645  
646  
647  
648  
649  
650  
651  
652  
653  
654  
655  
656  
657  
658  
659  
660  
661  
662  
663  
664  
665  
666  
667  
668  
669  
670  
671  
672  
673  
674  
675  
676  
677  
678  
679  
680  
681  
682  
683  
684  
685  
686  
687  
688  
689  
690  
691  
692  
693  
694  
695  
696  
697  
698  
699  
700  
701  
702  
703  
704  
705  
706  
707  
708  
709  
710  
711  
712  
713  
714  
715  
716  
717  
718  
719  
720  
721  
722  
723  
724  
725  
726  
727  
728  
729  
730  
731  
732  
733  
734  
735  
736  
737  
738  
739  
740  
741  
742  
743  
744  
745  
746  
747  
748  
749  
750  
751  
752  
753  
754  
755  
756  
757  
758  
759  
760  
761  
762  
763  
764  
765  
766  
767  
768  
769  
770  
771  
772  
773  
774  
775  
776  
777  
778  
779  
780  
781  
782  
783  
784  
785  
786  
787  
788  
789  
790  
791  
792  
793  
794  
795  
796  
797  
798  
799  
800  
801  
802  
803  
804  
805  
806  
807  
808  
809  
810  
811  
812  
813  
814  
815  
816  
817  
818  
819  
820  
821  
822  
823  
824  
825  
826  
827  
828  
829  
830  
831  
832  
833  
834  
835  
836  
837  
838  
839  
840  
841  
842  
843  
844  
845  
846  
847  
848  
849  
850  
851  
852  
853  
854  
855  
856  
857  
858  
859  
860  
861  
862  
863  
864  
865  
866  
867  
868  
869  
870  
871  
872  
873  
874  
875  
876  
877  
878  
879  
880  
881  
882  
883  
884  
885  
886  
887  
888  
889  
890  
891  
892  
893  
894  
895  
896  
897  
898  
899  
900  
901  
902  
903  
904  
905  
906  
907  
908  
909  
910  
911  
912  
913  
914  
915  
916  
917  
918  
919  
920  
921  
922  
923  
924  
925  
926  
927  
928  
929  
930  
931  
932  
933  
934  
935  
936  
937  
938  
939  
940  
941  
942  
943  
944  
945  
946  
947  
948  
949  
950  
951  
952  
953  
954  
955  
956  
957  
958  
959  
960  
961  
962  
963  
964  
965  
966  
967  
968  
969  
970  
971  
972  
973  
974  
975  
976  
977  
978  
979  
980  
981  
982  
983  
984  
985  
986  
987  
988  
989  
990  
991  
992  
993  
994  
995  
996  
997  
998  
999  
1000  
1001  
1002  
1003  
1004  
1005  
1006  
1007  
1008  
1009  
1010  
1011  
1012  
1013  
1014  
1015  
1016  
1017  
1018  
1019  
1020  
1021  
1022  
1023  
1024  
1025  
1026  
1027  
1028  
1029  
1030  
1031  
1032  
1033  
1034  
1035  
1036  
1037  
1038  
1039  
1040  
1041  
1042  
1043  
1044  
1045  
1046  
1047  
1048  
1049  
1050  
1051  
1052  
1053  
1054  
1055  
1056  
1057  
1058  
1059  
1060  
1061  
1062  
1063  
1064  
1065  
1066  
1067  
1068  
1069  
1070  
1071  
1072  
1073  
1074  
1075  
1076  
1077  
1078  
1079  
1080  
1081  
1082  
1083  
1084  
1085  
1086  
1087  
1088  
1089  
1090  
1091  
1092  
1093  
1094  
1095  
1096  
1097  
1098  
1099  
1100  
1101  
1102  
1103  
1104  
1105  
1106  
1107  
1108  
1109  
1110  
1111  
1112  
1113  
1114  
1115  
1116  
1117  
1118  
1119  
1120  
1121  
1122  
1123  
1124  
1125  
1126  
1127  
1128  
1129  
1130  
1131  
1132  
1133  
1134  
1135  
1136  
1137  
1138  
1139  
1140  
1141  
1142  
1143  
1144  
1145  
1146  
1147  
1148  
1149  
1150  
1151  
1152  
1153  
1154  
1155  
1156  
1157  
1158  
1159  
1160  
1161  
1162  
1163  
1164  
1165  
1166  
1167  
1168  
1169  
1170  
1171  
1172  
1173  
1174  
1175  
1176  
1177  
1178  
1179  
1180  
1181  
1182  
1183  
1184  
1185  
1186  
1187  
1188  
1189  
1190  
1191  
1192  
1193  
1194  
1195  
1196  
1197  
1198  
1199  
1200  
1201  
1202  
1203  
1204  
1205  
1206  
1207  
1208  
1209  
1210  
1211  
1212  
1213  
1214  
1215  
1216  
1217  
1218  
1219  
1220  
1221  
1222  
1223  
1224  
1225  
1226  
1227  
1228  
1229  
1230  
1231  
1232  
1233  
1234  
1235  
1236  
1237  
1238  
1239  
1240  
1241  
1242  
1243  
1244  
1245  
1246  
1247  
1248  
1249  
1250  
1251  
1252  
1253  
1254  
1255  
1256  
1257  
1258  
1259  
1260  
1261  
1262  
1263  
1264  
1265  
1266  
1267  
1268  
1269  
1270  
1271  
1272  
1273  
1274  
1275  
1276  
1277  
1278  
1279  
1280  
1281  
1282  
1283  
1284  
1285  
1286  
1287  
1288  
1289  
1290  
1291  
1292  
1293  
1294  
1295  
1296  
1297  
1298  
1299  
1300  
1301  
1302  
1303  
1304  
1305  
1306  
1307  
1308  
1309  
1310  
1311  
1312  
1313  
1314  
1315  
1316  
1317  
1318  
1319  
1320  
1321  
1322  
1323  
1324  
1325  
1326  
1327  
1328  
1329  
1330  
1331  
1332  
1333  
1334  
1335  
1336  
1337  
1338  
1339  
1340  
1341  
1342  
1343  
1344  
1345  
1346  
1347  
1348  
1349  
1350  
1351  
1352  
1353  
1354  
1355  
1356  
1357  
1358  
1359  
1360  
1361  
1362  
1363  
1364  
1365  
1366  
1367  
1368  
1369  
1370  
1371  
1372  
1373  
1374  
1375  
1376  
1377  
1378  
1379  
1380  
1381  
1382  
1383  
1384  
1385  
1386  
1387  
1388  
1389  
1390  
1391  
1392  
1393  
1394  
1395  
1396  
1397  
1398  
1399  
1400  
1401  
1402  
1403  
1404  
1405  
1406  
1407  
1408  
1409  
1410  
1411  
1412  
1413  
1414  
1415  
1416  
1417  
1418  
1419  
1420  
1421  
1422  
1423  
1424  
1425  
1426  
1427  
1428  
1429  
1430  
1431  
1432  
1433  
1434  
1435  
1436  
1437  
1438  
1439  
1440  
1441  
1442  
1443  
1444  
1445  
1446  
1447  
1448  
1449  
1450  
1451  
1452  
1453  
1454  
1455  
1456  
1457  
1458  
1459  
1460  
1461  
1462  
1463  
1464  
1465  
1466  
1467  
1468  
1469  
1470  
1471  
1472  
1473  
1474  
1475  
1476  
1477  
1478  
1479  
1480  
1481  
1482  
1483  
1484  
1485  
1486  
1487  
1488  
1489  
1490  
1491  
1492  
1493  
1494  
1495  
1496  
1497  
1498  
1499  
1500  
1501  
1502  
1503  
1504  
1505  
1506  
1507  
1508  
1509  
1510  
1511  
1512  
1513  
1514  
1515  
1516  
1517  
1518  
1519  
1520  
1521  
1522  
1523  
1524  
1525  
1526  
1527  
1528  
1529  
1530  
1531  
1532  
1533  
1534  
1535  
1536  
1537  
1538  
1539  
1540  
1541  
1542  
1543  
1544  
1545  
1546  
1547  
1548  
1549  
1550  
1551  
1552  
1553  
1554  
1555  
1556  
1557  
1558  
1559  
1560  
1561  
1562  
1563  
1564  
1565  
1566  
1567  
1568  
1569  
1570  
1571  
1572  
1573  
1574  
1575  
1576  
1577  
1578  
1579  
1580  
1581  
1582  
1583  
1584  
1585  
1586  
1587  
1588  
1589  
1590  
1591  
1592  
1593  
1594  
1595  
1596  
1597  
1598  
1599  
1600  
1601  
1602  
1603  
1604  
1605  
1606  
1607  
1608  
1609  
1610  
1611  
1612  
1613  
1614  
1615  
1616  
1617  
1618  
1619  
1620  
1621  
1622  
1623  
1624  
1625  
1626  
1627  
1628  
1629  
1630  
1631  
1632  
1633  
1634  
1635  
1636  
1637  
1638  
1639  
1640  
1641  
1642  
1643  
1644  
1645  
1646  
1647  
1648  
1649  
1650  
1651  
1652  
1653  
1654  
1655  
1656  
1657  
1658  
1659  
1660  
1661  
1662  
1663  
1664  
1665  
1666  
1667  
1668  
1669  
1670  
1671  
1672  
1673  
1674  
1675  
1676  
1677  
1678  
1679  
1680  
1681  
1682  
1683  
1684  
1685  
1686  
1687  
1688  
1689  
1690  
1691  
1692  
1693  
1694  
1695  
1696  
1697  
1698  
1699  
1700  
1701  
1702  
1703  
1704  
1705  
1706  
1707  
1708  
1709  
1710  
1711  
1712  
1713  
1714  
1715  
1716  
1717  
1718  
1719  
1720  
1721  
1722  
1723  
1724  
1725  
1726  
1727  
1728  
1729  
1730  
1731  
1732  
1733  
1734  
1735  
1736  
1737  
1738  
1739  
1740  
1741  
1742  
1743  
1744  
1745  
1746  
1747  
1748  
1749  
1750  
1751  
1752  
1753  
1754  
1755  
1756  
1757  
1758  
1759  
1760  
1761  
1762  
1763  
1764  
1765  
1766  
1767  
1768  
1769  
1770  
1771  
1772  
1773  
1774  
1775  
1776  
1777  
1778  
1779  
1780  
1781  
1782  
1783  
1784  
1785  
1786  
1787  
1788  
1789  
1790  
1791  
1792  
1793  
1794  
1795  
1796  
1797  
1798  
1799  
1800  
1801  
1802  
1803  
1804  
1805  
1806  
1807  
1808  
1809  
1810  
1811  
1812  
1813  
1814  
1815  
1816  
1817  
1818  
1819  
1820  
1821  
1822  
1823  
1824  
1825  
1826  
1827  
1828  
1829  
1830  
1831  
1832  
1833  
1834  
1835  
1836  
1837  
1838  
1839  
1840  
1841  
1842  
1843  
1844  
1845  
1846  
1847  
1848  
1849  
1850  
1851  
1852  
1853  
1854  
1855  
1856  
1857  
1858  
1859  
1860  
1861  
1862  
1863  
1864  
1865  
1866  
1867  
1868  
1869  
1870  
1871  
1872  
1873  
1874  
1875  
1876  
1877  
1878  
1879  
1880  
1881  
1882  
1883  
1884  
1885  
1886  
1887  
1888  
1889  
1890  
1891  
1892  
1893  
1894  
1895  
1896  
1897  
1898  
1899  
1900  
1901  
1902  
1903  
1904  
1905  
1906  
1907  
1908  
1909  
1910  
1911  
1912  
1913  
1914  
1915  
1916  
1917  
1918  
1919  
1920  
1921  
1922  
1923  
1924  
1925  
1926  
1927  
1928  
1929  
1930  
1931  
1932  
1933  
1934  
1935  
1936  
1937  
1938  
1939  
1940  
1941  
1942  
1943  
1944  
1945  
1946  
1947  
1948  
1949  
1950  
1951  
1952  
1953  
1954  
1955  
1956  
1957  
1958  
1959  
1960  
1961  
1962  
1963  
1964  
1965  
1966  
1967  
1968  
1969  
1970  
1971  
1972  
1973  
1974  
1975  
1976  
1977  
1978  
1979  
1980  
1981  
1982  
1983  
1984  
1985  
1986  
1987  
1988  
1989  
1990  
1991  
1992  
1993  
1994  
1995  
1996  
1997  
1998  
1999  
2000  
2001  
2002  
2003  
2004  
2005  
2006  
2007  
2008  
2009  
2010  
2011  
2012  
2013  
2014  
2015  
2016  
2017  
2018  
2019  
2020  
2021  
2022  
2023  
2024  
2025  
2026  
2027  
2028  
2029  
2030  
2031  
2032  
2033  
2034  
2035  
2036  
2037  
2038  
2039  
2040  
2041  
2042  
2043  
2044  
2045  
2046  
2047  
2048  
2049  
2050  
2051  
2052  
2053  
2054  
2055  
2056  
2057  
2058  
2059  
2060  
2061  
2062  
2063  
2064  
2065  
2066  
2067  
2068  
2069  
2070  
2071  
2072  
2073  
2074  
2075  
2076  
2077  
2078  
2079  
2080  
2081  
2082  
2083  
2084  
2085  
2086  
2087  
2088  
2089  
2090  
2091  
2092  
2093  
2094  
2095  
2096  
2097  
2098  
2099  
2100  
2101  
2102  
2103  
2104  
2105  
2106  
2107  
2108  
2109  
2110  
2111  
2112  
2113  
2114  
2115  
2116  
2117  
2118  
2119  
2120  
2121  
2122  
2123  
2124  
2125  
2126  
2127  
2128  
2129  
2130  
2131  
2132  
2133  
2134  
2135  
2136  
2137  
2138  
2139  
2140  
2141  
2142  
2143  
2144  
2145  
2146  
2147  
2148  
2149  
2150  
2151  
2152  
2153  
2154  
2155  
2156  
2157  
2158  
2159  
2160  
2161  
2162  
2163  
2164  
2165  
2166  
2167  
2168  
2169  
2170  
2171  
2172  
2173  
2174  
2175  
2176  
2177  
2178  
2179  
2180  
2181  
2182  
2183  
2184  
2185  
2186  
2187  
2188  
2189  
2190  
2191  
2192  
2193  
2194  
2195  
2196  
2197  
2198  
2199  
2200  
2201  
2202  
2203  
2204  
2205  
2206  
2207  
2208  
2209  
2210  
2211  
2212  
2213  
2214  
2215  
2216  
2217  
2218  
2219  
2220  
2221  
2222  
2223  
2224  
2225  
2226  
2227  
2228  
2229  
2230  
2231  
2232  
2233  
2234  
2235  
2236  
2237  
2238  
2239  
2240  
2241  
22